Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of PTGL18AR4R7M6B72B0 from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=PTGL18AR4R7M6B72B0

# PTGL18AR4R7M6B72B0










## **Applications**

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
Specific Applications	Industrial Equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	



## Appearance & Shape







## Packaging Information

Packaging	Specifications	Standard Packing Quantity
В0	Bulk(Bag)	100



### **Features**

- 1. Best suited to meet the requirements for power supplies and motor protection. Error-free operations are assured by rush current.
- 2. Circuit is protected until current is turned off.
- 3. Restores the original low resistance value automatically once the overload is removed.
- 4. Non-contact design leads to long life and no noise. Durable and strong against mechanical vibration and shock because it is a solid element.

1 of 3

### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of PTGL18AR4R7M6B72B0 from the official website of Murata

# PTGL18AR4R7M6B72B0



# **Specifications**


Max. Voltage	125V
Hold Current(25°C)	450mA
Hold Current (2)	360mA
Measure Condition of Hold Current (2)	(at +60°C)
Trip Current(25°C)	775mA
Trip Current(2)	900mA
Measure Condition of Trip Current(2)	(at -10°C)
Max. Current	1.7A
Resistance (25°C)	4.7Ω
Resistance Value Tolerance (at 25°C)	±20%
Curie Point(typ.)	120°C
Power Consumption(typ)	3.1W
Operating Temperature Range	-10°C to 60°C
D- Outer Dimension	18.5mm
Thickness	5.5mm
F- Lead Space	7.5mm
d- Lead Diameter	0.6mm
Shape	Lead
Mass	3.55g
MSL	N

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Please download the latest datasheet of PTGL18AR4R7M6B72B0 from the official website of Murata

# PTGL18AR4R7M6B72B0




### **Product Data**





### Resistance-Temperature Charac.



### Operating Time (Typical Curve)

### Protective Threshold Current Range

3 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

