

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCD188R71H102KA01	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H102MA01	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A102KA01	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A102MA01	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H122KA01	1200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H122MA01	1200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A122KA01	1200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A122MA01	1200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H152KA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H152MA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A152KA01	1500 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H182KA01	1800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H182MA01	1800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A182KA01	1800 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A182MA01	1800 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H222KA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H222MA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A222KA01	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A222MA01	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H272KA01	2700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H272MA01	2700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A272KA01	2700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A272MA01	2700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H332KA01	3300 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H332MA01	3300 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A332KA01	3300 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A332MA01	3300 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H392KA01	3900 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H392MA01	3900 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A392KA01	3900 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A392MA01	3900 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H472KA01	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R71H472MA01	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A472KA01	4700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	Powertrain/Safety for Automotive	AEC-Q200 100 Hz - 6 GHz
GCD188R72A472MA01	4700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%</		

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCD21BR71H563KA01	56000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H563MA01	56000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A563KA01	56000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A563MA01	56000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H683KA01	68000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H683MA01	68000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A683KA01	68000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A683MA01	68000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H823KA01	82000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H823MA01	82000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A823KA01	82000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A823MA01	82000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H104KA01	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR71H104MA01	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A104KA01	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BR72A104MA01	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCD21BC71C474KE01	470000 pF	16Vdc	X7S (EIA)	0805 (2012M)	1.4	± 10%	Powertrain/ Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCE18BR71H102KA01	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H102MA01	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A102KA01	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A102MA01	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H122KA01	1200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H122MA01	1200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A122KA01	1200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A122MA01	1200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H152KA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H152MA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A152KA01	1500 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A152MA01	1500 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H182KA01	1800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H182MA01	1800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A182KA01	1800 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A182MA01	1800 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H222KA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR71H222MA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	nal electrode for Powertrain/ safety for Automotive	100 Hz - 6 GHz
GCE18BR72A222KA01								

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCE21BR72A273MA01	27000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H433KA01	33000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H333MA01	33000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A333KA01	33000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A333MA01	33000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H393KA01	39000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H393MA01	39000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A393KA01	39000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A393MA01	39000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H473KA01	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H473MA01	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A473KA01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A473MA01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H563KA01	56000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H563MA01	56000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A563KA01	56000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A563MA01	56000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H683KA01	68000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H683MA01	68000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A683KA01	68000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A683MA01	68000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H823KA01	82000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H823MA01	82000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A823KA01	82000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A823MA01	82000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H104KA01	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR71H104MA01	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A104KA01	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCE21BR72A104MA01	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCH033R61E221KE01	220 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Implantable medical device	100 Hz ~ 6 GHz
GCH033R61E102KE01	1000 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Implantable medical device	100 Hz ~ 6 GHz
GCH033R71E102KE01	1000 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Implantable medical device	100 Hz ~ 6 GHz
GCH033R61E222KE01	2200 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Implantable medical device	100 Hz ~ 6 GHz
GCH033R61A472KE01	4700 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Implantable medical device	100 Hz ~ 6 GHz
GCH033R61A103KE01	10000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Implantable medical device	100 Hz ~ 6 GHz
GCH155R71H221KE01	220 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Implantable medical device	

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCJ188R71E152MA01	1500 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H152KA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H152MA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A152KA01	1500 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A152MA01	1500 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R92A152KA01	1500 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H182KA01	1800 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71E182KA01	1800 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H182KA01	1800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A182KA01	1800 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R92A182KA01	1800 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H222KA01	2200 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H222MA01	2200 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71E222KA01	2200 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71E222MA01	2200 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H222KA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H222MA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A222KA01	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A222MA01	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R92A222KA01	2200 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H272KA01	2700 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71E272KA01	2700 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H272KA01	2700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A272KA01	2700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R92A272KA01	2700 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H332KA01	3300 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71E332KA01	3300 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H332KA01	3300 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A332KA01	3300 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R92A332KA01	3300 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H392KA01	3900 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71E392KA01	3900 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R71H392KA01	3900 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R72A392KA01	3900 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188R92A392KA01	3900 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ188L81H472KA01	4700 pF	50Vdc	X8L (MURATA)	0603 (1608M)				

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (Simulation model)
GCJ188L81C393KA01	39000 pF	16Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81E393KA01	39000 pF	25Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81YA393KA01	39000 pF	35Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71C393KA01	39000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71E393KA01	39000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71H393KA12	39000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R92A393KA01	39000 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81C473KA01	47000 pF	16Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81C473MA01	47000 pF	16Vdc	X8L (MURATA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71C473KA01	47000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71E473KA01	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71H473KA12	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71H473MA12	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R92A473KA01	47000 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R92A473MA01	47000 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81E563KA01	56000 pF	25Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81YA563KA01	56000 pF	35Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71C563KA01	56000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71E563KA12	56000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71H563KA12	56000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R92A563KA01	56000 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81C683KA01	68000 pF	16Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81C683MA01	68000 pF	16Vdc	X8L (MURATA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81E683KA01	68000 pF	25Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81E683MA01	68000 pF	25Vdc	X8L (MURATA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81YA683KA01	68000 pF	35Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81YA683MA01	68000 pF	35Vdc	X8L (MURATA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71C683KA01	68000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71E683KA12	68000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71E683MA12	68000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71H683KA12	68000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71H683MA12	68000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R92A683KA01	68000 pF	100Vdc	X8R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188L81E823KA01	82000 pF	25Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71C823KA01	82000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ188R71E823KA12								

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCJ216R71H821KA01	820 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ219R72A821KA01	820 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E102KA01	1000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E102MA01	1000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H102KA01	1000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H102MA01	1000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A102KA01	1000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A102MA01	1000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A122KA01	1200 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A152KA01	1500 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A182KA01	1800 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E222KA01	2200 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E222MA01	2200 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H222KA01	2200 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H222MA01	2200 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A222KA01	2200 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A222MA01	2200 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A272KA01	2700 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E332KA01	3300 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E332MA01	3300 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H332KA01	3300 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H332MA01	3300 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A332KA01	3300 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A332MA01	3300 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A392KA01	3900 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E472KA01	4700 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E472MA01	4700 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H472KA01	4700 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H472MA01	4700 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A472KA01	4700 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A472MA01	4700 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R72A562KA01	5600 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E682KA01	6800 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71E682MA01	6800 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H682KA01	6800 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	nal electrode for Powertrain/safety for Automotive	100 Hz - 6 GHz
GCJ216R71H682MA01	6800 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7			

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCJ21BL81E274KA01	270000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C274KA01	270000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E274KA01	270000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ219R71E334KA01	330000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ219R71H334KA12	330000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ219R71H334MA12	330000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81E334KA01	330000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81E334MA01	330000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL8YA334KA01	330000 pF	35Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL8YA334MA01	330000 pF	35Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C334KA01	330000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C334MA01	330000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E334KA01	330000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E334MA01	330000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71H334KA12	330000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71H334MA12	330000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81E394KA01	390000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C394KA01	390000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E394KA01	390000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ219R71E474KA12	470000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ219R71E474MA12	470000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81E474KA01	470000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL8EH474KA07	470000 pF	50Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL8YA474KA01	470000 pF	35Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81C564KA01	560000 pF	16Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C564KA01	560000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E564KA12	560000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81C684KA01	680000 pF	16Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81C684MA01	680000 pF	16Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81E684KA01	680000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BL81E684MA01	680000 pF	25Vdc	X8L (MURATA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C684KA01	680000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71C684MA01	680000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	± 20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E684KA12	680000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ21BR71E684MA12	680000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	± 20		

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCJ31GR71H225MA12	2.2 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31MLB1C225KA01	2.2 uF	16Vdc	X8L (MURATA)	1206 (3216M)	1.35	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31MLB1C225MA01	2.2 uF	16Vdc	X8L (MURATA)	1206 (3216M)	1.35	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31CLB1C335KA01	3.3 uF	50Vdc	X8L (MURATA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GC71H475KA01	4.7 uF	50Vdc	X7S (EIA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GC71H475MA01	4.7 uF	50Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31CLB1C475KA01	4.7 uF	16Vdc	X8L (MURATA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31CLB1C475MA01	4.7 uF	16Vdc	X8L (MURATA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71C475MA01	4.7 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71E475MA12	4.7 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GC71E106KA15	10 uF	25Vdc	X7S (EIA)	1206 (3216M)	2	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GC71E108MA15	10 uF	25Vdc	X7S (EIA)	1206 (3216M)	2	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71A108MA13	10 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71C106KA15	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71C108MA15	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31CLBED228KE07	22 uF	10Vdc	X8L (MURATA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR70J228KE01	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR70J228ME01	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71A228KE01	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.9	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ31GR71A228ME01	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32DLBEL225KA07	2.2 uF	100Vdc	X8L (MURATA)	1210 (3225M)	2.3	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32DR72A225KA01	2.2 uF	100Vdc	X7R (EIA)	1210 (3225M)	2.3	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32DR72A225MA01	2.2 uF	100Vdc	X7R (EIA)	1210 (3225M)	2.3	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32DC72A475KE01	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.3	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32EL81E475KA01	4.7 uF	25Vdc	X8L (MURATA)	1210 (3225M)	2.8	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32EL81E475MA01	4.7 uF	25Vdc	X8L (MURATA)	1210 (3225M)	2.8	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER71H475KA12	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.8	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER71H475MA12	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.8	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER91C885KE01	6.8 uF	16Vdc	X8R (EIA)	1210 (3225M)	2.8	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32EC71H106KA01	10 uF	50Vdc	X7S (EIA)	1210 (3225M)	2.8	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32EC71H108MA01	10 uF	50Vdc	X7S (EIA)	1210 (3225M)	2.8	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER91C106KE01	10 uF	16Vdc	X8R (EIA)	1210 (3225M)	2.8	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER91C108ME01	10 uF	16Vdc	X8R (EIA)	1210 (3225M)	2.8	±20%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32EC71E228KE02	22 uF	25Vdc	X7S (EIA)	1210 (3225M)	2.85	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32EL8EF228KE08	22 uF	25Vdc	X8L (MURATA)	1210 (3225M)	2.85	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER71C228KE01	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.8	±10%	hal electrode for Powertrain/safety for Automotive	100 Hz ~ 6 GHz
GCJ32ER71C228ME01	22 uF	16Vdc	X7R (EIA)	1210				

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCM155R72A222KA01	2200 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11H332KA01	3300 pF	50Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R72A332KA01	3300 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155L81H472KA01	4700 pF	50Vdc	X8L (MURATA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11H472KA01	4700 pF	50Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R72A472KA01	4700 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11E682KA01	6800 pF	25Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11H682KA40	6800 pF	50Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155L81E103KA01	10000 pF	25Vdc	X8L (MURATA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11E103KA01	10000 pF	25Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11H103KA40	10000 pF	50Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11E153KA40	15000 pF	25Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71H153KA40	15000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155L81C223KA01	22000 pF	16Vdc	X8L (MURATA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11E223KA40	22000 pF	25Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71H223KA40	22000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11C333KA01	33000 pF	16Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R1E333KA40	33000 pF	25Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71H333KE01	33000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155L81C473KA01	47000 pF	16Vdc	X8L (MURATA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11C473KA01	47000 pF	16Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R1E473KA40	47000 pF	25Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71H473KE01	47000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R1C683KA40	68000 pF	16Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71H683KE01	68000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155L81E104KE01	100000 pF	25Vdc	X8L (MURATA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11A104KA01	100000 pF	10Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R11C104KA40	100000 pF	16Vdc	R (JIS)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71A104KA01	100000 pF	10Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71H104KE37	100000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155R71C224KE01	220000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155C71A474KE35	470000 pF	10Vdc	X7S (EIA)	0402 (1005M)	0.6	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155C71A474ME35	470000 pF	10Vdc	X7S (EIA)	0402 (1005M)	0.6	± 20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155C71A684KE39	680000 pF	10Vdc	X7S (EIA)	0402 (1005M)	0.7	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155C71A684ME39	680000 pF	10Vdc	X7S (EIA)	0402 (1005M)	0.7	± 20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155C71A105KE39	1 uF	10Vdc	X7S (EIA)	0402 (1005M)	0.7	± 10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM155C71A105ME39	1 uF	10Vdc	X7S (EIA					

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm (mm))	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCM188R72A682KA01	6800 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E103KA01	10000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H103KA01	10000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R72A103KA01	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E153KA01	15000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H153KA01	15000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R72A153KA01	15000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E223KA01	22000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H223KA01	22000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R72A223KA01	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E333KA01	33000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H333KA40	33000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188L81H473KA40	47000 pF	50Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E473KA01	47000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H473KA40	47000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E683KA42	68000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H683KA42	68000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11C104KA01	100000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E104KA42	100000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11H104KA42	100000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E154KA01	150000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71H154KA49	150000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188L81C224KA01	220000 pF	16Vdc	X8L (MURATA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11A224KA01	220000 pF	10Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11C224KA01	220000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11E224KA40	220000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71H224KA49	220000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11C334KA01	330000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R11C474KA40	470000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71E474KA49	470000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM18D71H105KE35	1 uF	50Vdc	X7T (EIA)	0603 (1608M)	1	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM18D7YA105KE35	1 uF	35Vdc	X7T (EIA)	0603 (1608M)	1	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71C105KA49	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71C105MA49	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71E105KA49	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188R71E105MA49	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188C71A225KE01	2.2 uF	10Vdc	X7S (EIA)	0603 (1608M)	0.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM188C71A225ME01	2.2 uF							

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCM21BR72A104KA01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	±1%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11E154KA01	15000 pF	25Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11H154KA01	15000 pF	50Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R1C224KA01	22000 pF	16Vdc	R (JIS)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11E224KA01	22000 pF	25Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11H224KA01	22000 pF	50Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R1C334KA01	33000 pF	25Vdc	R (JIS)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R71H334KA40	33000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R1A474KA01	47000 pF	10Vdc	R (JIS)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R1E474KA40	47000 pF	25Vdc	R (JIS)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11C474KA01	47000 pF	16Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71H474KA40	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R1C684KA01	68000 pF	16Vdc	R (JIS)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR1E684KA40	68000 pF	25Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR7YA684KA40	68000 pF	35Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM219R1C105KA01	1 uF	16Vdc	R (JIS)	0805 (2012M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC72A105KE35	1 uF	100Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC72A105ME35	1 uF	100Vdc	X7S (EIA)	0805 (2012M)	1.45	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11A105KA01	1 uF	10Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR11E105KA42	1 uF	25Vdc	R (JIS)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71H105KA01	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR7YA105KA40	1 uF	35Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71E155KA36	1.5 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71E155MA36	1.5 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR7YA155KA36	1.5 uF	35Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC7YA225KE01	2.2 uF	35Vdc	X7S (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BD71H225KE35	2.2 uF	50Vdc	X7T (EIA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71A225KA01	2.2 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71C225KA49	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71E225KA67	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC71A475KA67	4.7 uF	10Vdc	X7S (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC71E475KE35	4.7 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC7YA475KE35	4.7 uF	35Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71C475KA67	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC71C106KE35	10 uF	16Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BC71E106KE36	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BD70J106KE02	10 uF	6.3Vdc	X7T (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BM8EE106KE08	10 uF	16Vdc	X8M (MURATA)	0805 (2012M)	1.45	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR70J106KE22	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BR71A106KE22	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BD70G226ME36	22 uF	4Vdc	X7T (EIA)	0805 (2012M)	1.45	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM21BD70J226ME36	22 uF	6.3Vdc	X7T (EIA)	0805 (2012)	1.45	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM319R72A104KA01	10000 pF	100Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR72A154KA01	15000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR72A224KA01	22000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11H334KA01	33000 pF	50Vdc	R (JIS)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11H474KA01	47000 pF	50Vdc	R (JIS)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CR11H684KA01	68000 pF	50Vdc	R (JIS)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CL81H105KA40	1 uF	50Vdc	X8L (MURATA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CR72A105KA01	1 uF	100Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CR91E105KA01	1 uF	25Vdc	X8R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31ML81E105KA01	1 uF	25Vdc	X8L (MURATA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11C105KA01	1 uF	16Vdc	R (JIS)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11E105KA01	1 uF	25Vdc	R (JIS)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR71H105KA40	1 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CC72A225KE01	2.2 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CC72A225ME01	2.2 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CR71H225KA40	2.2 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11A225KA36	2.2 uF	10Vdc	R (JIS)	1206 (3216M)	1.3	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11C225KA36	2.2 uF	16Vdc	R (JIS)	1206 (3216M)	1.3	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31MR11E225KA42	2.2 uF	25Vdc	R (JIS)	1206 (3216M)	1.3	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CC71H475KA49	4.7 uF	50Vdc	X7S (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CR11C475KA01	4.7 uF	16Vdc	R (JIS)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CR71E475KA40	4.7 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CC71E106KA01	10 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz
GCM31CD71H106KF35	10 uF	50Vdc	X7T (EIA)	1206 (3216M)	1.9	±10%	Powertrain/Safety for Automotive	100 Hz ~ 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GCM31CD7YA106KE35	10 uF	35Vdc	X7T (EIA)	1206 (3216M)	1.9	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CR11A106KA49	10 uF	10Vdc	R (JIS)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CR71C106KA49	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CC71C226ME35	22 uF	16Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CR70J226KE26	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CR70J226ME26	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CR71A226KE01	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM31CD70G476ME01	47 uF	4Vdc	X7T (EIA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM319R72A104KA37	100000 pF	100Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR72A154KA37	150000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR72A224KA37	220000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR71H334KA37	330000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR71H474KA37	470000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR71H684KA55	680000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CL81H105KA55	1 uF	50Vdc	X8L (MURATA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR72A105KA03	1 uF	100Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR91E105KA37	1 uF	25Vdc	X8R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31ML81E105KA37	1 uF	25Vdc	X8L (MURATA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR71E105KA37	1 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR71H105KA55	1 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CC72A225KE02	2.2 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CC72A225ME02	2.2 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CL8EL225KE07	2.2 uF	100Vdc	X8L (MURATA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR71H225KA55	2.2 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31MR71E225KA57	2.2 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.3	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CC71H475KA03	4.7 uF	50Vdc	X7S (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR71C475KA37	4.7 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR71E475KA55	4.7 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CC71E106KA03	10 uF	25Vdc	X7S (EIA)	1206 (3216M)	1.9	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CD7YA106KE36	10 uF	35Vdc	X7T (EIA)	1206 (3216M)	1.9	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR71A106KA64	10 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR71C106KA64	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CC71C226ME36	22 uF	16Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR70J226ME23	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CR71A226KE02	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CD70G476ME02	47 uF	4Vdc	X7T (EIA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM31CM8EB476ME07	47 uF	4Vdc	X8M (MURATA)	1206 (3216M)	1.8	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER11A226ME11	1 uF	50Vdc	R (JIS)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32RR11E105KA01	1 uF	25Vdc	R (JIS)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32DC72A475KE01	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32DC72A475ME01	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32DR11E475KA40	4.7 uF	25Vdc	R (JIS)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER71H475KA40	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32DR11C106KA01	10 uF	16Vdc	R (JIS)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32EC71H106KA01	10 uF	50Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32EC7YA106KA01	10 uF	35Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER71E106KA42	10 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32EC71E226KE35	22 uF	25Vdc	X7S (EIA)	1210 (3225M)	2.85	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER11A226KE11	22 uF	10Vdc	R (JIS)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER11A226ME11	22 uF	10Vdc	R (JIS)	1210 (3225M)	2.7	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER71C226ME15	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32EC71A476KE01	47 uF	10Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER70J476KE16	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER70J476ME16	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ED70E227ME35	220 uF	2.5Vdc	X7T (EIA)	1210 (3225M)	2.85	±20%	Powertrain/Safety for Automotive	100 Hz - 6 GHz
GCM32ER71H105KA37	1 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32DC72A475KE02	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32DC72A475ME02	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32DL8EL475KE07	4.7 uF	100Vdc	X8L (MURATA)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32DR71E475KA55	4.7 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER71H475KA55	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32DR71C106KA37	10 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.2	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EC71H106KA03	10 uF	50Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EC7YA106KA03	10 uF	35Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EL8EH106KA07	10 uF	50Vdc	X8L (MURATA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER71E106KA57	10 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EC71E226KE36	22 uF	25Vdc	X7S (EIA)	1210 (3225M)	2.85	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EL8EF226KE08	22 uF	25Vdc	X8L (MURATA)	1210 (3225M)	2.85	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER71A226KE12	22 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER71A226ME12	22 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER71C226KE19	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER71C226ME19	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EC71A476KE02	47 uF	10Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER70J476KE19	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ER70J476ME19	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ED70E107ME36	100 uF	2.5Vdc	X7T (EIA)	1210 (3225M)	2.85	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32ED70E227ME36	220 uF	2.5Vdc	X7T (EIA)	1210 (3225M)	2.85	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GCM32EM8EA227ME08	220 uF	2.5Vdc	X8M (MURATA)	1210 (3225M)	2.85	±20%	Powertrain/Safety for Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R71H102KA02	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R72A102KA02	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R71H222KA02	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R72A222KA02	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R71H472KA02	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R72A472KA02	4700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R71H103KA02	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R72A103KA02	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R71H223KA02	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R72A223KA02	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD188R71E473KA02	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD21BR71H473KA02	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD21BR72A473KA02	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD21BR71H104KA02	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGD21BR72A104KA02	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/MLSC/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H221KA37	220 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R72A221KA37	220 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H471KA37	470 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R72A471KA37	470 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H102KA37	1000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R72A102KA37	1000 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H222KA37	2200 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R72A222KA37	2200 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71E472KA37	4700 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H472KA37	4700 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R72A472KA37	4700 pF	100Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71E103KA37	10000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H103KA55	10000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71E223KA55	22000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Automotive [AEC-Q200]	100 Hz - 6 GHz
GGM155R71H223KA55	22000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55			

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GGM188R72A103KA37	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R72A223KA37	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R71E224KA55	220000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R71H224KA64	220000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R71C474KA55	470000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R71E474KA64	470000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R71C105KA56	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R71E105KA64	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM188R70J225KE22	2.2 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR72A473KA37	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR72A104KA37	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71H224KA37	220000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71E474KA55	470000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71H474KA55	470000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71C105KA37	1 uF	16Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BC72A105KE36	1 uF	100Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71E105KA56	1 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71H105KA03	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR7YA105KA55	1 uF	35Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BC7YA225KE02	2.2 uF	35Vdc	X7S (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71A225KA37	2.2 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71C225KA64	2.2 uF	18Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71E225KA73	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BC71A475KA73	4.7 uF	10Vdc	X7S (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BC71E475KE36	4.7 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BC7YA475KE36	4.7 uF	35Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71C475KA73	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR70J106KE22	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM21BR71A106KE22	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31MR72A224KA37	220000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31C072A225KE02	2.2 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31CR71H225KA55	2.2 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31C071H475KA03	4.7 uF	50Vdc	X7S (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31CR71C475KA37	4.7 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31CR71E475KA55	4.7 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31C071E106KA03	10 uF	25Vdc	X7S (EIA)	1206 (3216M)	1.9	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31CR71C106KA64	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31CR70J226KE23	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM31CR71A226KE02	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32DC72A475KE02	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32ER71H475KA55	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32EC71H106KA03	10 uF	50Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32EC7YA106KA03	10 uF	35Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32ER71E106KA57	10 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32ER71A226KE12	22 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32ER71C226KE19	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GGM32ER70J476KE19	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Automotive AEC-Q200	100 Hz - 6 GHz
GJ431CC81E105JA01	1 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±5%	Audio signal low distortion	100 Hz - 6 GHz
GJ431CC81E105KA01	1 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Audio signal low distortion	100 Hz - 6 GHz
GJ431CC81E105MA01	1 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	Audio signal low distortion	100 Hz - 6 GHz
GJ821BB31H105KA12	1 uF	50Vdc	B (JIS)	0805 (2012M)	1.35	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GJ821BR71H105KA12	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GJ831CC81E105KA01	1 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GJ831R61H225KA12	2.2 uF	50Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GJ831CR71H475KA12	4.7 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GJ831CR61E106KEB3	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.9	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GJ832ER7YA106KA12	10 uF	35Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Acoustic noise reduction	100 Hz - 6 GHz
GRJ033R60J105ME11	1 uF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.35	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ033R61A105ME11	1 uF	10Vdc	X5R (EIA)	0201 (0603M)	0.35	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ155R60J106ME11	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H102KE11	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H102ME11	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A102KE11	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A102ME11	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H222KE11	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H222ME11	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A222KE11	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A222ME11	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H472KE11	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H472ME11	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A472KE11	4700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A472ME11	4700 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H103KE11	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H103ME11	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A103KE11	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A103ME11	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H223KE11	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H223ME11	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A223KE11	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A223ME11	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71E473KE11	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71E473ME11	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71H473KE11	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71H473ME11	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71H104KE11	100000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71H104ME11	100000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R72A104KE11	100000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 kHz - 6 GHz
GRJ188R72A104ME11	100000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71E224KE11	220000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71E224ME11	220000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71H224KE11	220000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71H224ME11	220000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71C474KE11	470000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 kHz - 6 GHz
GRJ188R71C474ME11	470000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 kHz - 6 GHz
GRJ188R61C105KE11	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R61C105ME11	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R6YA105KE11	1 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71E105KE11	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R71E105ME11	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R70J225KE11	2.2 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R70J225ME11	2.2 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188C70J475KE11	4.7 uF	6.3Vdc	X7S (EIA)	0603 (1608M)	1	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188C70J475ME11	4.7 uF	6.3Vdc	X7S (EIA)	0603 (1608M)	1	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R60J475KE11	4.7 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R60J475ME11	4.7 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R61A475KE11	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ188R61A475ME11	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R60J106ME11	10 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ188R61A106ME11	10 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Resin external electrode	100 Hz - 6 GHz
GRJ219R72A221KE01	220 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	Resin external electrode	100 Hz - 6 GHz
GRJ219R72A221ME01	220 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.95	±20%	Resin external electrode	1

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (Simulation model)
GRJ21BR72A102KE01	100 nF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A102ME01	1000 nF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H222KE01	2200 nF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H222ME01	2200 nF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A222KE01	2200 nF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A222ME01	2200 nF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H472KE01	4700 nF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H472ME01	4700 nF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A472KE01	4700 nF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A472ME01	4700 nF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H103KE01	10000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A103KE01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A103ME01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H223KE01	22000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H223ME01	22000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A223KE01	22000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A223ME01	22000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H473KE01	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H473ME01	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A473KE01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR72A473ME01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H224KE01	220000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 kHz ~ 6 GHz
GRJ21BR71H224ME01	220000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 kHz ~ 6 GHz
GRJ21BR71H474KE01	470000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 kHz ~ 6 GHz
GRJ21BR71H474ME01	470000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 kHz ~ 6 GHz
GRJ21BC72A105KE11	1 uF	100Vdc	X7S (EIA)	0805 (2012M)	1.5	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BC72A105ME11	1 uF	100Vdc	X7S (EIA)	0805 (2012M)	1.5	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71E105KE11	1 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71E105ME11	1 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H105KE01	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71H105ME01	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71E225KE01	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71E225ME01	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71C475KE01	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71C475ME01	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.45	±20%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR61E106KE01	10 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ21BR71A106KE01	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.45	±10%	Resin external electrode	100 Hz ~ 6 GHz
GRJ319R71H104KE11	100000 pF	50Vdc	X7R					

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM011R61A331KE01	330 pF	10Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R61A331ME01	330 pF	10Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R61A471KE01	470 pF	10Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R61A471ME01	470 pF	10Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R61A681KE01	680 pF	10Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R61A681ME01	680 pF	10Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J102KE01	1000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J102ME01	1000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J152KE01	1500 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J152ME01	1500 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J222KE01	2200 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J222ME01	2200 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G332KE01	3300 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J332KE01	3300 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J332ME01	3300 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G472KE01	4700 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J472KE01	4700 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J472ME01	4700 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G682KE01	6800 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J682KE01	6800 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J682ME01	6800 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G103KE01	10000 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J103KE01	10000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J103ME01	10000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011C80E223KE01	22000 pF	2.5Vdc	X6S (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011C80E223ME01	22000 pF	2.5Vdc	X6S (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G223KE01	22000 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G223ME01	22000 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J223KE01	22000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J223ME01	22000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011C80E473KE01	47000 pF	2.5Vdc	X6S (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011C80E473ME01	47000 pF	2.5Vdc	X6S (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G473KE01	47000 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60G473ME01	47000 pF	4Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J473KE01	47000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 10%	Ultra-small	100 Hz ~ 6 GHz
GRM011R60J473ME01	47000 pF	6.3Vdc	X5R (EIA)	080804 (0201M)	0.138	± 20%	Ultra-small	100 Hz ~ 6 GHz
GRM011C80E104ME01	100							

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM022R71C102KE14	1000 pF	16Vdc	X7R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R71C102ME14	1000 pF	16Vdc	X7R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J152KE19	1500 pF	6.3Vdc	B (JIS)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J152ME19	1500 pF	6.3Vdc	B (JIS)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022B31A152KE19	1500 pF	10Vdc	B (JIS)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B31A152ME19	1500 pF	10Vdc	B (JIS)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J152KE19	1500 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J152ME19	1500 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61A152KE19	1500 pF	10Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61C152KE01	1500 pF	16Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61C152ME01	1500 pF	16Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J182KE19	1800 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J222KE19	2200 pF	6.3Vdc	B (JIS)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J222ME19	2200 pF	6.3Vdc	B (JIS)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022B31A222KE19	2200 pF	10Vdc	B (JIS)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B31A222ME19	2200 pF	10Vdc	B (JIS)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022C71A222KE19	2200 pF	10Vdc	X7S (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022C81C222KE01	2200 pF	16Vdc	X6S (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J222KE19	2200 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J222ME19	2200 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61A222KE19	2200 pF	10Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61A222ME19	2200 pF	10Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61C222KE01	2200 pF	16Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61C222ME01	2200 pF	16Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J332KE19	3300 pF	6.3Vdc	B (JIS)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J332ME19	3300 pF	6.3Vdc	B (JIS)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022B31A332KE19	3300 pF	10Vdc	B (JIS)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B31A332ME19	3300 pF	10Vdc	B (JIS)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022C71A332KE19	3300 pF	10Vdc	X7S (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022C81C332KE01	3300 pF	16Vdc	X6S (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J332KE19	3300 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J332ME19	3300 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61A332KE19	3300 pF	10Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61A332ME19	3300 pF	10Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61C332KE01	3300 pF	16Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022R61C332ME01	3300 pF	16Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J382KE19	3900 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM022B30J472KE19	4700 pF	6.3Vdc	B (JIS)	01005				

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM022D80G474ME01	470000 pF	4Vdc	X6T (EIA)	01005 (0402M)	0.25	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60G474ME15	470000 pF	4Vdc	X5R (EIA)	01005 (0402M)	0.25	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J474ME05	470000 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.22	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60J474ME15	470000 pF	6.3Vdc	X5R (EIA)	01005 (0402M)	0.25	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM022R60G105ME01	1 uF	4Vdc	X5R (EIA)	01005 (0402M)	0.25	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM033B11C101KA01	100 pF	16Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B11E101KA01	100 pF	25Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B31H101KA12	100 pF	50Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B31H101MA12	100 pF	50Vdc	B (JIS)	0201 (0603M)	0.33	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM033R11C101KA01	100 pF	16Vdc	R (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R11E101KA01	100 pF	25Vdc	R (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R61E101KA01	100 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71C101KA01	100 pF	16Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71E101KA01	100 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71H101KA12	100 pF	50Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71H101MA12	100 pF	50Vdc	X7R (EIA)	0201 (0603M)	0.33	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71E121KA01	120 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B11C151KA01	150 pF	16Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B11E151KA01	150 pF	25Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B31H151KA12	150 pF	50Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B31H151MA12	150 pF	50Vdc	B (JIS)	0201 (0603M)	0.33	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM033R11C151KA01	150 pF	16Vdc	R (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R11E151KA01	150 pF	25Vdc	R (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R61E151KA01	150 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71C151KA01	150 pF	16Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71E151KA01	150 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71H151KA12	150 pF	50Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71H151MA12	150 pF	50Vdc	X7R (EIA)	0201 (0603M)	0.33	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM033B11C221KA01	220 pF	16Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B11E221KA01	220 pF	25Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B31H221KA12	220 pF	50Vdc	B (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033B31H221MA12	220 pF	50Vdc	B (JIS)	0201 (0603M)	0.33	±20%	Ultra-small	100 Hz ~ 6 GHz
GRM033R11C221KA01	220 pF	16Vdc	R (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R11E221KA01	220 pF	25Vdc	R (JIS)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R61E221KA01	220 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R61H221KA12	220 pF	50Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71C221KA01	220 pF	16Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71E221KA01	220 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Ultra-small	100 Hz ~ 6 GHz
GRM033R71H221KA12	220 pF	50Vdc						

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM155Z71A225KE44	2.2 uF	10Vdc	X7R (MURATA)	0402 (1005M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM155Z71A225ME43	2.2 uF	10Vdc	X7R (MURATA)	0402 (1005M)	0.55	±20%	General Purpose	100 Hz - 6 GHz
GRM153R60G475ME15	4.7 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.33	±20%	General Purpose	100 Hz - 6 GHz
GRM153R60G475ME15	4.7 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.33	±20%	General Purpose	100 Hz - 6 GHz
GRM155B30G475ME47	4.7 uF	4Vdc	B (JIS)	0402 (1005M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM155B30G475ME87	4.7 uF	4Vdc	B (JIS)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155B30G475ME47	4.7 uF	6.3Vdc	B (JIS)	0402 (1005M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM155B30G475ME87	4.7 uF	6.3Vdc	B (JIS)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155C61E475ME15	4.7 uF	25Vdc	X5S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80J475ME01	4.7 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80J475MEAA	4.7 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155C81A475ME01	4.7 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155D70G475ME15	4.7 uF	4Vdc	X7T (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155D70J475ME15	4.7 uF	6.3Vdc	X7T (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155D71A475ME15	4.7 uF	10Vdc	X7T (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155D80E475ME47	4.7 uF	2.5Vdc	X6T (EIA)	0402 (1005M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM155D81A475ME15	4.7 uF	10Vdc	X6T (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155D81C475ME15	4.7 uF	16Vdc	X6T (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60E475ME76	4.7 uF	2.5Vdc	X5R (EIA)	0402 (1005M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G475ME47	4.7 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G475ME87	4.7 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J475ME47	4.7 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J475ME87	4.7 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R61A475ME01	4.7 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R61A475MEAA	4.7 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R61C475ME01	4.7 uF	16Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80E106ME16	10 uF	2.5Vdc	X5S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80E106ME44	10 uF	2.5Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80G106ME18	10 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80G106ME44	10 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80J106ME18	10 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155D70G106ME18	10 uF	4Vdc	X7T (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60E106ME16	10 uF	2.5Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G106ME01	10 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G106ME15	10 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G106ME47	10 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.5	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J106ME05	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J106ME15	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J106ME18	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J106ME47	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.5	±20%	General Purpose	100 Hz - 6 GHz
GRM155R61A106ME11	10 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R61A106ME18	10 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80E156ME01	15 uF	2.5Vdc	X6S (EIA)	0402 (1005M)	0.5	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80G156ME05	15 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G156ME01	15 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.5	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G156ME15	15 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J156ME15	15 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G186ME01	18 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J186ME01	18 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80E226ME11	22 uF	2.5Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60G226ME11	22 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155R60J226ME11	22 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM155C80G226ME01	22 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM158R60J226ME01	22 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM158R61A226ME15	22 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM188B11H221KA01	220 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H221MA01	220 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11H221KA01	220 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	500 kHz - 6 GHz
GRM188R11H221MA01	220 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	500 kHz - 6 GHz
GRM188R71H221KA01	220 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H221MA01	220 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R72A221KA01	220 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R72A221MA01	220 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188B11H331KA01	330 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H331MA01	330 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11H331KA01	330 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H331KA01	330 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R72A331KA01	330 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H471KA01	470 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H471MA01	470 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11H471KA01	470 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R11H471MA01	470 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R71H471JA01	470 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±5%	General Purpose	100 Hz - 6 GHz
GRM188R71H471KA01	470 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H471MA01	470 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R72A471KA01	470 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R72A471MA01	470 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188B11H681KA01	680 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H681MA01	680 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11H681KA01	680 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H681KA01	680 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R72A681KA01	680 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11E102KA01	1000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H102KA01	1000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H102MA01	1000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11E102KA01	1000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz - 6 GHz
GRM188R11H102KA01	1000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz - 6 GHz
GRM188R11H102MA01	1000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 kHz - 6 GHz
GRM188R61H102KA01	1000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz - 6 GHz
GRM188R71E102KA01	1000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H102KA01	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H102MA01	1000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R72A102KA01	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R72A102MA01	1000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188B11E152KA01	1500 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H152KA01	1500 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R11E152KA01	1500 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R11H152KA01	1500 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71E152KA01	1500 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H152KA01	1500 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R72A152KA01	1500 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H182KA01	1800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11E222KA01	2200 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H222KA01	2200 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188B11H222MA01	2200 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188B11H222MA01	2200 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11E222KA01	2200 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R11H222MA01	2200 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R11H222MA01	2200 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R61H222KA01	2200 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71E222KA01	2200 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H222MA01	2200 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R71H222JA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±5%	General Purpose	100 Hz - 6 GHz
GRM188R71H222KA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R71H222MA01	2200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM188R72A222KA01	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R72A222MA01	2200 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71E272KA01	2700 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E332KA01	3300 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H332KA01	3300 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H332MA01	3300 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E332KA01	3300 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11H332KA01	3300 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E332KA01	3300 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H332KA01	3300 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R72A332KA01	3300 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H392KA01	3900 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E472KA01	4700 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E472MA01	4700 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11H472KA01	4700 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H472MA01	4700 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E472KA01	4700 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11E472MA01	4700 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11H472KA01	4700 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11H472MA01	4700 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R61H472KA01	4700 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E472KA01	4700 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E472MA01	4700 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H472JA01	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 5%	General Purpose	100 Hz - 6 GHz
GRM188R71H472KA01	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H472MA01	4700 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H562KA01	5600 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E682KA01	6800 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H682KA01	6800 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H682MA01	6800 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E682KA01	6800 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11H682KA01	6800 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E682KA01	6800 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H682KA01	6800 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H822KA01	8200 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E103KA01	10000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E103MA01	10000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11H103KA01	10000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H103MA01	10000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E103KA01	10000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 kHz - 6 GHz
GRM188R11E103MA01	10000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 kHz - 6 GHz
GRM188R11H103KA01	10000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 kHz - 6 GHz
GRM188R11H103MA01	10000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 kHz - 6 GHz
GRM188R61H103KA01	10000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E103KA01	10000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E103MA01	10000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H103JA01	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 5%	General Purpose	100 Hz - 6 GHz
GRM188R71H103KA01	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H103MA01	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R72A103KA01	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R72A103MA01	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H123JA01	12000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 5%	General Purpose	100 Hz - 6 GHz
GRM188R71H123KA01	12000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E153KA01	15000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E153MA01	15000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11H153KA01	15000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H153MA01	15000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E153KA01	15000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11H153KA01	15000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E153KA01	15000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H153JA01	15000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 5%	General Purpose	100 Hz - 6 GHz
GRM188R71H153KA01	15000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R72A153KAC4	15000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R72A153MAC4	15000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H183KA01	18000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E223KA01	22000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E223MA01	22000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 kHz - 6 GHz
GRM188B11H223KA01	22000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H223MA01	22000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E223KA01	22000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 kHz - 6 GHz
GRM188R11E223MA01	22000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 kHz - 6 GHz
GRM188R11H223KA01	22000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 kHz - 6 GHz
GRM188R11H223MA01	22000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 kHz - 6 GHz
GRM188R61H223KA01	22000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E223KA01	22000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E223MA01	22000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 kHz - 6 GHz
GRM188R71H223KA01	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H223MA01	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R72A223JAC4	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 5%	General Purpose	100 Hz - 6 GHz
GRM188R72A223KAC4	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R72A223MAC4	22000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H273KA61	27000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E333KA01	33000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E333MA01	33000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11H333KA61	33000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H333MA61	33000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E333KA01	33000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 kHz - 6 GHz
GRM188R11H333KA61	33000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E333KA01	33000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H333KA61	33000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H393KA61	39000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E473KA01	47000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E473MA01	47000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11H473KA61	47000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11H473MA61	47000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E473KA01	47000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11E473MA01	47000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11H473KA61	47000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R11H473MA61	47000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71C473JA01	47000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	± 5%	General Purpose	100 Hz - 6 GHz
GRM188R71E473KA01	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E473MA01	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R71H473KA61	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H473MA61	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11E683KA01	68000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E683MA01	68000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B31H683KA92	68000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B31H683MA92	68000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188R11E683KA01	68000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 kHz - 6 GHz
GRM188R11H683KA93	68000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E683KA01	68000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71H683KA93	68000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188R71E823KA01	82000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11C104KA01	100000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11C104MA01	100000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	± 20%	General Purpose	100 Hz - 6 GHz
GRM188B11E104KA01	100000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	± 10%	General Purpose	100 Hz - 6 GHz
GRM188B11E104MA01	100000 pF	25Vdc</						

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM18B331H104KA92	10000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331H104MA92	10000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C104KA01	10000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E104KA01	10000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E104MA01	10000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11H104KA93	10000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11H104MA93	10000 pF	50Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C104KA01	10000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61E104KA01	10000 pF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B70J104KA01	10000 pF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C104KA01	10000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C104MA01	10000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E104KA01	10000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E104MA01	10000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71H104KA93	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71H104MA93	10000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B72A104KA35	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B72A104MA35	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C154KA01	15000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E154KA01	15000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331H154KA01	15000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331H154MA01	15000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C154KA01	15000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E154KA01	15000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A154KA01	15000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C154KA01	15000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E154KA01	15000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71H154KA01	15000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71H154MA01	15000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A224KA01	22000 pF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz ~ 6 GHz
GRM18B11C224KA01	22000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C224MA01	22000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E224KA87	22000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E224MA87	22000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331H224KA01	22000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331H224MA01	22000 pF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A224KA01	22000 pF	10Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz ~ 6 GHz
GRM18B11C224KA01	22000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C224MA01	22000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E224KA88	22000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E224MA88	22000 pF	25Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61A224KA01	22000 pF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz ~ 6 GHz
GRM18B61C224KA88	22000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61E224KA88	22000 pF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61H224KA01	22000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B70J224KA88	22000 pF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A224JA01	22000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±5%	General Purpose	100 kHz ~ 6 GHz
GRM18B71A224KA01	22000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 kHz ~ 6 GHz
GRM18B71C224KA01	22000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C224MA01	22000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E224JA88	22000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±5%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E224KA88	22000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E224MA88	22000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71H224KA01	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71H224MA01	22000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A334KA61	33000 pF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A334MA61	33000 pF	10Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C334KA01	33000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C334MA01	33000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11E334KA01	33000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61A334KA61	33000 pF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61A334MA61	33000 pF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A334KA61	33000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A334MA61	33000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C334KA01	33000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B10J474KA01	47000 pF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A474KA61	47000 pF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C474KA75	47000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C474KA87	47000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C474MA75	47000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C474MA87	47000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E474KA75	47000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E474MA75	47000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C474KA88	47000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11C474MA88	47000 pF	16Vdc	R (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B60J474KA01	47000 pF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61A474KA61	47000 pF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C474KA12	47000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C474KA93	47000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C474MA12	47000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C474MA93	47000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61E474KA12	47000 pF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61E474MA12	47000 pF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61H474KA12	47000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61H474MA12	47000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B70J474KA01	47000 pF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A474KA61	47000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A474MA61	47000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C474KA88	47000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71C474MA88	47000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E474KA12	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71E474MA12	47000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B7YA474KE05	47000 pF	35Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B7YA474ME05	47000 pF	35Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A684KA61	68000 pF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B11A684MA61	68000 pF	10Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C684KA75	68000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C684MA75	68000 pF	16Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E684KA75	68000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E684MA75	68000 pF	25Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61A684KA61	68000 pF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61A684MA61	68000 pF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C684KA75	68000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61C684MA75	68000 pF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61E684KA75	68000 pF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B61E684MA75	68000 pF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B61H684KA75	68000 pF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A684KA61	68000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B71A684MA61	68000 pF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B30J105KE25	1 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331A105KE35	1 uF	10Vdc	B (JIS)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C105KE43	1 uF	16Vdc	B (JIS)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331C105ME43	1 uF	16Vdc	B (JIS)	0603 (1608M)	0.5	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E105KA12	1 uF	25Vdc	B (JIS)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM18B331E105MA12	1 uF	25Vdc	B (JIS)	0603 (1608M)	0.5	±20%	General Purpose	100 Hz ~ 6 GHz
GRM18C60J105KF26	1 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM185C81A105KE36	1 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185D71A105KE36	1 uF	10Vdc	X7T (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185R60J105KE26	1 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185R61C105KE44	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185R61C105ME44	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.5	±20%	General Purpose	100 Hz ~ 6 GHz
GRM185R61E105KA12	1 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185R61E105MA12	1 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.5	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B10J105KA01	1 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B11A105KA61	1 uF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31C105KA92	1 uF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31C105MA92	1 uF	16Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B31E105KA75	1 uF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31E105MA75	1 uF	25Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B31H105KAAL	1 uF	50Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31H105MAAL	1 uF	50Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C80G105MA01	1 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C81A105KA12	1 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81C105KA12	1 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81C105MA12	1 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C81E105KA12	1 uF	25Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81E105KAAD	1 uF	25Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81E105MAAD	1 uF	25Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C8YA105KAAL	1 uF	35Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188D71H105KE01	1 uF	50Vdc	X7T (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188D71H105ME01	1 uF	50Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188D72A105KE01	1 uF	100Vdc	X7T (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188D72A105ME01	1 uF	100Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R60J105KA01	1 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R60J105MA01	1 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61A105KA61	1 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61A105MA61	1 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61C105KA12	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61C105KA93	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61C105MA12	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61C105MA93	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61E105KA12	1 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61E105KAAD	1 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61E105MA12	1 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61H105KAAL	1 uF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61H105MAAL	1 uF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R6YA105KA12	1 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R6YA105KAAL	1 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R70J105KA01	1 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R70J105MA01	1 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R71A105KA61	1 uF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R71C105KA12	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R71C105KE15	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R71C105MA12	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R71C105ME15	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R71E105KA12	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R71E105MA12	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R7YA105KA12	1 uF	35Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R7YA105MA12	1 uF	35Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM185R60J225KE26	2.2 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.5	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B30J225KE18	2.2 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31A225KE33	2.2 uF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31A225ME33	2.2 uF	10Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B31C225KE14	2.2 uF	16Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31E225KE14	2.2 uF	25Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31E225MA12	2.2 uF	25Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B3YA225KE18	2.2 uF	35Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B3YA225MA12	2.2 uF	35Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C71C225KE11	2.2 uF	16Vdc	X7S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C71C225ME11	2.2 uF	16Vdc	X7S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C71E225KE11	2.2 uF	25Vdc	X7S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C71E225ME11	2.2 uF	25Vdc	X7S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C80J225KE19	2.2 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C80J225ME19	2.2 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C81A225KAAD	2.2 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81A225KE34	2.2 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81A225ME34	2.2 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C81C225KA12	2.2 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81C225MA12	2.2 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C81E225KE11	2.2 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81E225ME11	2.2 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C8YA225KE11	2.2 uF	35Vdc	X6S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C8YA225ME11	2.2 uF	35Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R60J225KE19	2.2 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61A225KE34	2.2 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61A225ME34	2.2 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61C225KAAD	2.2 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61C225KE15	2.2 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61E225KA12	2.2 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61E225MA12	2.2 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61H225KE11	2.2 uF	50Vdc	X5R (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R61H225ME11	2.2 uF	50Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R6YA225KA12	2.2 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R6YA225MA12	2.2 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R70J225KE15	2.2 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R71A225KE15	2.2 uF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188R71A225ME15	2.2 uF	10Vdc	X7R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188Z71C225KE43	2.2 uF	16Vdc	X7R (MURATA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188Z71C225ME43	2.2 uF	16Vdc	X7R (MURATA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188Z71E225KE43	2.2 uF	25Vdc	X7R (MURATA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188Z71E225ME43	2.2 uF	25Vdc	X7R (MURATA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188R61A335KE15	3.3 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185C80J475ME11	4.7 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.55	±20%	General Purpose	100 Hz ~ 6 GHz
GRM185C81A475KE11	4.7 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.55	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185C81A475ME11	4.7 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.55	±20%	General Purpose	100 Hz ~ 6 GHz
GRM185D70J475ME11	4.7 uF	6.3Vdc	X7T (EIA)	0603 (1608M)	0.55	±20%	General Purpose	100 Hz ~ 6 GHz
GRM185R61A475KE11	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.55	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185R61A475ME11	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.55	±20%	General Purpose	100 Hz ~ 6 GHz
GRM185R61C475KE11	4.7 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.55	±10%	General Purpose	100 Hz ~ 6 GHz
GRM185R61C475ME11	4.7 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.55	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B30J475KE18	4.7 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B30J475ME18	4.7 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B30J475ME84	4.7 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B31A475KE15	4.7 uF	10Vdc	B (JIS)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31A475ME15	4.7 uF	10Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188B31C475KAAJ	4.7 uF	16Vdc	B (JIS)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188B31C475MAAJ	4.7 uF	16Vdc	B (JIS)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C71A475KE11	4.7 uF	10Vdc	X7S (EIA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C71A475ME11	4.7 uF	10Vdc	X7S (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C71C475KE21	4.7 uF	16Vdc	X7S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C71C475ME21	4.7 uF	16Vdc	X7S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM188C81C475KE11	4.7 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM188C81C475ME11	4.7 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM188C81E475KE11	4.7 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188C81E475ME11	4.7 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D71A475KE11	4.7 uF	10Vdc	X7T (EIA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM188D71A475ME11	4.7 uF	10Vdc	X7T (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J475KE19	4.7 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R60J475ME19	4.7 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J475ME84	4.7 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61A475KAAJ	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM188R61A475KE15	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R61A475MAAJ	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61A475ME15	4.7 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61C475KE11	4.7 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM188R61C475ME11	4.7 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61E475KE11	4.7 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM188R61E475ME11	4.7 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R6YA475KE15	4.7 uF	35Vdc	X5R (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188R6YA475ME15	4.7 uF	35Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188Z71A475KE15	4.7 uF	10Vdc	X7R (MURATA)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM188Z71A475ME15	4.7 uF	10Vdc	X7R (MURATA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188Z71C475KE21	4.7 uF	16Vdc	X7R (MURATA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188Z71C475ME21	4.7 uF	16Vdc	X7R (MURATA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM185R60G106ME15	10 uF	4Vdc	X5R (EIA)	0603 (1608M)	0.5	±20%	General Purpose	100 Hz - 6 GHz
GRM185R60J106ME15	10 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.5	±20%	General Purpose	100 Hz - 6 GHz
GRM188B30G106ME46	10 uF	4Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188B30J106ME47	10 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188B30J106ME84	10 uF	6.3Vdc	B (JIS)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188B31A106KE69	10 uF	10Vdc	B (JIS)	0603 (1608M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM188B31A106ME69	10 uF	10Vdc	B (JIS)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80E106KE47	10 uF	2.5Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188C80E106ME47	10 uF	2.5Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80G106ME47	10 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80G106ME69	10 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80J106KA73	10 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80J106MEA6	10 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188C81A106KA73	10 uF	10Vdc	X6S (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188C81A106ME73	10 uF	10Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C81C106KA73	10 uF	16Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D70J106KA73	10 uF	6.3Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D71A106KA73	10 uF	10Vdc	X7T (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188D71A106ME73	10 uF	10Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60G106ME47	10 uF	4Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J106KE47	10 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	General Purpose	100 Hz - 6 GHz
GRM188R60J106ME47	10 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J106ME84	10 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61A106MAAL	10 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61A106ME69	10 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61C106KA73	10 uF	16Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61C106MAAL	10 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61E106KA73	10 uF	25Vdc	X5R (EIA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188R61E106ME73	10 uF	25Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R6YA106KA73	10 uF	35Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188Z71A106KA73	10 uF	10Vdc	X7R (MURATA)	0603 (1608M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM188Z71A106ME73	10 uF	10Vdc	X7R (MURATA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM186R60G226ME15	22 uF	4Vdc	X5R (EIA)	0603 (1608M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM186R60J226ME15	22 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.6	±20%	General Purpose	100 Hz - 6 GHz
GRM187R60J226ME15	22 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM187R61A226ME15	22 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM188B30G226MEA0	22 uF	4Vdc	B (JIS)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188B30J226MEA0	22 uF	6.3Vdc	B (JIS)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C60J226MEA0	22 uF	6.3Vdc	X5S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C61C226ME01	22 uF	16Vdc	X5S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C61E226ME01	22 uF	25Vdc	X5S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80G226ME15	22 uF	4Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80J226ME01	22 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80J226ME15	22 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C81A226ME01	22 uF	10Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D70E226ME01	22 uF	2.5Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D70G226ME01	22 uF	4Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D70J226ME01	22 uF	6.3Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60G226MEA0	22 uF	4Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J226ME15	22 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J226MEA0	22 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R61A226ME15	22 uF	10Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80E476ME05	47 uF	2.5Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188C80G476ME01	47 uF	4Vdc	X6S (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188D70E476ME01	47 uF	2.5Vdc	X7T (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60E476ME15	47 uF	2.5Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60G476ME01	47 uF	4Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60G476ME15	47 uF	4Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J476ME01	47 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM188R60J476ME15	47 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM216R71H472KA01	4700 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM216R71H682KA01	6800 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM219R72A682KA01	6800 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM216R71H103KA01	10000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71H103KA01	10000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71H103MA01	10000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM219R72A103KA01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM219R72A103MA01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR72A103KA01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A103MA01	10000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz - 6 GHz
GRM216R71H123KA01	12000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71H153KA01	15000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71H153MA01	15000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR72A153KA01	15000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM216R71H223KA01	22000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM216R71H223MA01	22000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM219R71H223KA17	22000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71H223MA17	22000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR72A223KA01	22000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A223MA01	22000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz - 6 GHz
GRM219B11H333KA01	33000 pF	50Vdc	B (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM219R11H333KA01	33000 pF	50Vdc	R (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71H333KA01	33000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A333KA01	33000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BB11H473KA01	47000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BB11H473MA01	47000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR11H473KA01	47000 pF	50Vdc	R (JIS)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BR11H473MA01	47000 pF	50Vdc	R (JIS)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR71H473KA01	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H473MA01	47000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR72A473JA01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±5%	General Purpose	100 Hz - 6 GHz
GRM21BR72A473KA01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A473MA01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz - 6 GHz
GRM219R11E683KA01	68000 pF	25Vdc	R (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM219R71E683KA01	68000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM21BB11H683KA01	68000 pF	50Vdc	B (JIS)	0805 (				

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM21BR11H683KA01	68000 pF	50Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H683KA01	68000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A683KA04	68000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A683MAC4	68000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R71E104KA01	100000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71E104MA01	100000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB11H104KA01	100000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR11E104KA01	100000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 kHz - 6 GHz
GRM21BR11E104MA01	100000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 kHz - 6 GHz
GRM21BR11H104KA01	100000 pF	50Vdc	R (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71E104JA01	100000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.35	± 5%	General Purpose	100 Hz - 6 GHz
GRM21BR71E104KA01	100000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 kHz - 6 GHz
GRM21BR71E104MA01	100000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 kHz - 6 GHz
GRM21BR71H104KA01	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H104MA01	100000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR72A104KA04	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A104MAC4	100000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB11E154KA01	150000 pF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H154KA88	150000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H154MA88	150000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR11E154KA01	150000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR11E154MA01	150000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71E154KA01	150000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H154KA01	150000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71E224KA01	220000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM21AR72A224KAC5	220000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1	± 10%	General Purpose	100 Hz - 6 GHz
GRM21AR72A224MAC5	220000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB11C224KA01	220000 pF	16Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11C224MA01	220000 pF	16Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB11E224KA01	220000 pF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11E224MA01	220000 pF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31H224KA88	220000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H224MA88	220000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR11C224KA01	220000 pF	16Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR11C224MA01	220000 pF	16Vdc	R (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR11E224KA01	220000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR11E224MA01	220000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71C224KA01	220000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71C224MA01	220000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71E224KA01	220000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71E224MA01	220000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71H224KA01	220000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H224MA01	220000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM219B31H334KA87	330000 pF	50Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 kHz - 6 GHz
GRM219B31H334MA87	330000 pF	50Vdc	B (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 kHz - 6 GHz
GRM219R71C334KA88	330000 pF	16Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 kHz - 6 GHz
GRM219R71H334KA88	330000 pF	50Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 kHz - 6 GHz
GRM21AR72A334KAC5	330000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11E334KA01	330000 pF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71E334KA01	330000 pF	25Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31E474KA88	470000 pF	25Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31E474MA88	470000 pF	25Vdc	B (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R11E474KA88	470000 pF	25Vdc	R (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R11E474MA88	470000 pF	25Vdc	R (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R71C474KA01	470000 pF	16Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71E474KA88	470000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71E474MA88	470000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31H474KA87	470000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H474MA87	470000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR61C474KA01	470000 pF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71C474MA01	470000 pF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71H474KA88	470000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H474MA88	470000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR72A474KA73	470000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR72A474MA73	470000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM219B11C684KA01	680000 pF	16Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31E684KA88	680000 pF	25Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R11C684KA01	680000 pF	16Vdc	R (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71C684KA01	680000 pF	16Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71E684KA88	680000 pF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H684KA04	680000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H684MAC4	680000 pF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR11E684KA88	680000 pF	25Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM216B31C105KA87	1 uF	16Vdc	B (JIS)	0805 (2012M)	0.7	± 10%	General Purpose	100 Hz - 6 GHz
GRM216B31E105KA75	1 uF	25Vdc	B (JIS)	0805 (2012M)	0.7	± 10%	General Purpose	100 Hz - 6 GHz
GRM216C81C105KA12	1 uF	16Vdc	X6S (EIA)	0805 (2012M)	0.7	± 10%	General Purpose	100 Hz - 6 GHz
GRM216D71C105KA12	1 uF	16Vdc	X7T (EIA)	0805 (2012M)	0.7	± 10%	General Purpose	100 Hz - 6 GHz
GRM216D71C105MA12	1 uF	16Vdc	X7T (EIA)	0805 (2012M)	0.7	± 20%	General Purpose	100 Hz - 6 GHz
GRM216R61C105KA88	1 uF	16Vdc	X5R (EIA)	0805 (2012M)	0.7	± 10%	General Purpose	100 Hz - 6 GHz
GRM216R61E105KA12	1 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.7	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B11A105KA01	1 uF	10Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31E105KA88	1 uF	25Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31H105KA73	1 uF	50Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31H105MA73	1 uF	50Vdc	B (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R61A105KA01	1 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61H105KA73	1 uF	50Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61H105MA73	1 uF	50Vdc	X5R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R71E105KA88	1 uF	25Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R7YA105KA12	1 uF	35Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R7YA105MA12	1 uF	35Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB10J105KC01	1 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11A105KA01	1 uF	10Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11C105KA01	1 uF	16Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31E105KA98	1 uF	25Vdc	B (JIS)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H105KA12	1 uF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H105MA12	1 uF	50Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC72A105KE01	1 uF	100Vdc	X7S (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR10J105KC01	1 uF	6.3Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR11A105KA01	1 uF	10Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR11C105KA01	1 uF	16Vdc	R (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR11E105KA99	1 uF	25Vdc	R (JIS)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61A105KA01	1 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61C105KA01	1 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61H105KA12	1 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71A105KA01	1 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71C105KA01	1 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71E105KA99	1 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71H105KA12	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B11A225KA87	2.2 uF	16Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31E225KA75	2.2 uF	25Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31E225MA75	2.2 uF	25Vdc	B (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219B31H225KE15	2.2 uF	50Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31H225ME15	2.2 uF	50Vdc	B (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219C81C225KA12	2.2 uF	16Vdc	X6S (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch/mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM219C81E225KE15	2.2 uF	25Vdc	X6S (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219C81E225ME15	2.2 uF	25Vdc	X6S (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219C8YA225KE15	2.2 uF	35Vdc	X6S (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219C8YA225ME15	2.2 uF	35Vdc	X6S (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219D71C225KA12	2.2 uF	16Vdc	X7T (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219D71C225MA12	2.2 uF	16Vdc	X7T (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R61A225KA01	2.2 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61C225KA88	2.2 uF	16Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61E225KA12	2.2 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61E225MA12	2.2 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R61H225KE15	2.2 uF	50Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61H225ME15	2.2 uF	50Vdc	X5R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R71A225KE15	2.2 uF	10Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71A225ME15	2.2 uF	10Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R71C225KE15	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R71C225ME15	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB10J225KA01	2.2 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11A225KA01	2.2 uF	10Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB11A225MA01	2.2 uF	10Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31C225KA87	2.2 uF	16Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31E225KA75	2.2 uF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31E225MA75	2.2 uF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31H225KA73	2.2 uF	50Vdc	B (JIS)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H225MA73	2.2 uF	50Vdc	B (JIS)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC71E225KE11	2.2 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC71E225ME11	2.2 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC81E225KA12	2.2 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC8YA225KA73	2.2 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC8YA225MA73	2.2 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BD71H225KE01	2.2 uF	50Vdc	X7T (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BD72A225KE01	2.2 uF	100Vdc	X7T (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BD72A225ME01	2.2 uF	100Vdc	X7T (EIA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR60J225KA01	2.2 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61A225KA01	2.2 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61A225MA01	2.2 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR61C225KA88	2.2 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61E225KA12	2.2 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61H225KA73	2.2 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61H225MA73	2.2 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR70J225KA01	2.2 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71A225KA01	2.2 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71A225MA01	2.2 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71C225KA12	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71C225MA12	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71E225KE11	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71E225ME11	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R61A335KE19	3.3 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B30JA475KE18	4.7 uF	6.3Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31A475KE33	4.7 uF	10Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219B31A475ME33	4.7 uF	10Vdc	B (JIS)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219B31C475KE15	4.7 uF	16Vdc	B (JIS)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219C80JA475KE19	4.7 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219C81A475KE34	4.7 uF	10Vdc	X6S (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219C81A475ME34	4.7 uF	10Vdc	X6S (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219C81C475KA73	4.7 uF	16Vdc	X6S (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219C81C475MA73	4.7 uF	16Vdc	X6S (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219D71A475KE15	4.7 uF	10Vdc	X7T (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219D71A475ME15	4.7 uF	10Vdc	X7T (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R60JA475KE19	4.7 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61A475KE34	4.7 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61A475ME34	4.7 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R61C475KE15	4.7 uF	16Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61E475KA73	4.7 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R61E475MA73	4.7 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM219R6YA475KA73	4.7 uF	35Vdc	X5R (EIA)	0805 (2012M)	0.95	± 10%	General Purpose	100 Hz - 6 GHz
GRM219R6YA475MA73	4.7 uF	35Vdc	X5R (EIA)	0805 (2012M)	0.95	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB10JA475KA11	4.7 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB10JA475MA11	4.7 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31A475KA74	4.7 uF	10Vdc	B (JIS)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31A475MA74	4.7 uF	10Vdc	B (JIS)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31C475KA87	4.7 uF	16Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31E475KA75	4.7 uF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31E475MA75	4.7 uF	25Vdc	B (JIS)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BB31H475KE51	4.7 uF	50Vdc	B (JIS)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BB31H475ME51	4.7 uF	50Vdc	B (JIS)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC71E475KE11	4.7 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC71E475ME11	4.7 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC71H475KE11	4.7 uF	50Vdc	X7S (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC71H475ME11	4.7 uF	50Vdc	X7S (EIA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC7YA475KE11	4.7 uF	35Vdc	X7S (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC7YA475ME11	4.7 uF	35Vdc	X7S (EIA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC81C475KA88	4.7 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC81E475KA12	4.7 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC81E475MA12	4.7 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC81H475KE11	4.7 uF	50Vdc	X6S (EIA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC81H475ME11	4.7 uF	50Vdc	X6S (EIA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BC8YA475KE51	4.7 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BC8YA475ME51	4.7 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BD71C475KA12	4.7 uF	16Vdc	X7T (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BD71C475MA12	4.7 uF	16Vdc	X7T (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BE71C475KA12	4.7 uF	16Vdc	X7U (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BE71C475MA12	4.7 uF	16Vdc	X7U (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR60JA475KA11	4.7 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR60JA475MA11	4.7 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR61A475KA73	4.7 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61A475MA73	4.7 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR61C475KA88	4.7 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61E475KA12	4.7 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.35	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61E475ME12	4.7 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.35	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR61H475KE51	4.7 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR61H475ME51	4.7 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71A475KA73	4.7 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71A475KE51	4.7 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71A475MA73	4.7 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71A475ME51	4.7 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71C475KA73	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71C475ME51	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BR71E475KA73	4.7 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BR71E475MA73	4.7 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BZ71E475KE15	4.7 uF	25Vdc	X7R (MURATA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BZ71E475ME15	4.7 uF	25Vdc	X7R (MURATA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BZ71H475KE15	4.7 uF	50Vdc	X7R (MURATA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz
GRM21BZ71H475ME15	4.7 uF	50Vdc	X7R (MURATA)	0805 (2012M)	1.45	± 20%	General Purpose	100 Hz - 6 GHz
GRM21BZ7YA475KF15	4.7 uF	35Vdc	X7R (MURATA)	0805 (2012M)	1.45	± 10%	General Purpose	100 Hz - 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM21BZ7YA475ME15	4.7 uF	35Vdc	X7R (MURATA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B30J106KE18	10 uF	6.3Vdc	B (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219B30J106ME18	10 uF	6.3Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B31A106KE44	10 uF	10Vdc	B (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219B31A106ME44	10 uF	10Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B31C106KA73	10 uF	16Vdc	B (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219B31C106MA73	10 uF	16Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B31E106KA12	10 uF	25Vdc	B (JIS)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219B31E106MA12	10 uF	25Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219C80G106KE19	10 uF	4Vdc	X6S (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219C80G106ME19	10 uF	4Vdc	X6S (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219C80J106KE39	10 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219C80J106ME39	10 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R60J106KE19	10 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219R60J106ME19	10 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R61A106KE44	10 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219R61A106ME44	10 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R61A106ME47	10 uF	10Vdc	X5R (EIA)	0805 (2012M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R61C106KA73	10 uF	16Vdc	X5R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219R61C106MA73	10 uF	16Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R61E106KA12	10 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219R61E106MA12	10 uF	25Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB30J106KE18	10 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BB30J106ME18	10 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31A106KE18	10 uF	10Vdc	B (JIS)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31A106ME18	10 uF	10Vdc	B (JIS)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31C106KE15	10 uF	16Vdc	B (JIS)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31C106ME15	10 uF	16Vdc	B (JIS)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31D106KE15	10 uF	20Vdc	B (JIS)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31D106ME15	10 uF	20Vdc	B (JIS)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31E106KA73	10 uF	25Vdc	B (JIS)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31E106MA73	10 uF	25Vdc	B (JIS)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC70G106KE45	10 uF	4Vdc	X7S (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC71C106KE11	10 uF	16Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC71C106ME11	10 uF	16Vdc	X7S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC71E106KE01	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC71E106KE11	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC71E106ME01	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC71E106ME11	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80G106KE01	10 uF	4Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80G106ME19	10 uF	4Vdc	X6S (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80J106KE19	10 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80J106ME19	10 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81A106KE18	10 uF	10Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81A106ME18	10 uF	10Vdc	X6S (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81C106KA73	10 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81C106KE15	10 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81C106MA73	10 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81C106ME15	10 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81E106KE51	10 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81E106ME51	10 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC8YA106KE11	10 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BC8YA106ME11	10 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR60J106KE19	10 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR60J106ME19	10 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61A106KE19	10 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61A106ME19	10 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61C106KE15	10 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61C106ME15	10 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61D106KE15	10 uF	20Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61D106ME15	10 uF	20Vdc	X5R (EIA)	0805 (2012M)	1.35	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61E106KA73	10 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61E106MA73	10 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61H106KE43	10 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61H106ME43	10 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR6YA106KE43	10 uF	35Vdc	X5R (EIA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR6YA106ME43	10 uF	35Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR70J106KA73	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR70J106KE76	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR70J106MA73	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR70J106ME76	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR71A106KA73	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR71A106KE51	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BR71A106MA73	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR71A106ME51	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BZ71C106KE15	10 uF	16Vdc	X7R (MURATA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM21BZ71C106ME15	10 uF	16Vdc	X7R (MURATA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BZ71E106KE15	10 uF	25Vdc	X7R (MURATA)	0805 (2012M)	1.45	±10%	General Purpose	100 Hz ~ 6 GHz
GRM219B30G226ME66	22 uF	4Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B30J226ME47	22 uF	6.3Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B30J226MEA0	22 uF	6.3Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219B31A226MEA0	22 uF	10Vdc	B (JIS)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R60G226ME66	22 uF	4Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R60J226ME47	22 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R60J226MEA0	22 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R61A226MEA0	22 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R61C226ME15	22 uF	16Vdc	X5R (EIA)	0805 (2012M)	1	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB30J226ME38	22 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB31A226ME51	22 uF	10Vdc	B (JIS)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80G226ME39	22 uF	4Vdc	X6S (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80J226ME51	22 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81A226ME44	22 uF	10Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC81C226ME44	22 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BD70J226ME44	22 uF	6.3Vdc	X7T (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BD71A226ME44	22 uF	10Vdc	X7T (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BE70G226ME51	22 uF	4Vdc	X7U (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR60J226ME39	22 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61A226ME44	22 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61A226ME51	22 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.4	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61C226ME44	22 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61E226ME44	22 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BZ70J226ME44	22 uF	6.3Vdc	X7R (MURATA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BZ71A226ME15	22 uF	10Vdc	X7R (MURATA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219D80E476ME44	47 uF	2.5Vdc	X6T (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R60G476ME44	47 uF	4Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM219R60J476ME44	47 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB30G476ME15	47 uF	4Vdc	B (JIS)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BB30J476ME15	47 uF	6.3Vdc	B (JIS)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80G476ME15	47 uF	4Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80J476ME01	47 uF	6.3Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BD70E476ME01	47 uF	2.5Vdc	X7T (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BD80G476ME01	47 uF	4Vdc	X6T (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR60G476ME01	47 uF	4Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR60J476ME01	47 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR60J476ME11	47 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BR61A476ME15	47 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz
GRM21BC80E107ME15	100 uF	2.5Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz ~ 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM21BC80G107ME15	100 uF	4Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR60E107ME15	100 uF	2.5Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR60G107ME11	100 uF	4Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz - 6 GHz
GRM21BR60J107ME15	100 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	General Purpose	100 Hz - 6 GHz
GRM319R72A222KA01	2200 pF	100Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71H153KA01	15000 pF	50Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R72A153KA01	15000 pF	100Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71H223KA01	22000 pF	50Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A223KA01	22000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A223MA01	22000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR72A333KA01	33000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A473KA01	47000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A473MA01	47000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM319R71H683KA01	68000 pF	50Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A683KA01	68000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71H104JA01	100000 pF	50Vdc	X7R (EIA)	1206 (3216M)	0.95	±5%	General Purpose	100 Hz - 6 GHz
GRM319R72A104KA01	100000 pF	100Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11H154KA01	150000 pF	50Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11H154KA01	150000 pF	50Vdc	R (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71H154KA01	150000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A154KA01	150000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11E224KA01	220000 pF	25Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11E224MA01	220000 pF	25Vdc	B (JIS)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MB11H224KA01	220000 pF	50Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11H224MA01	220000 pF	50Vdc	B (JIS)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR11H224KA01	220000 pF	50Vdc	R (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11H224MA01	220000 pF	50Vdc	R (JIS)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR71H224KA01	220000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71H224MA01	220000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR72A224KA01	220000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11E334KA01	330000 pF	25Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R11E334KA01	330000 pF	25Vdc	R (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71E334KA01	330000 pF	25Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71H334KA01	330000 pF	50Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11C474KA01	470000 pF	16Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11C474MA01	470000 pF	16Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM319B11E474KA01	470000 pF	25Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11E474MA01	470000 pF	25Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM319R11E474KA01	470000 pF	25Vdc	R (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71E474KA01	470000 pF	25Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71E474KA01	470000 pF	25Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71H474JA01	470000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±5%	General Purpose	100 kHz - 6 GHz
GRM31MR71H474KA01	470000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71H474MA01	470000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR72A474KA35	470000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A474MA35	470000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.3	±20%	General Purpose	100 Hz - 6 GHz
GRM319B11E684KA01	680000 pF	25Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11C684KA01	680000 pF	16Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71H684KA88	680000 pF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR72A684KA35	680000 pF	100Vdc	X7R (EIA)	1206 (3216M)	1.3	±10%	General Purpose	100 kHz - 6 GHz
GRM319B11A105KA01	1 uF	10Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11C105KA01	1 uF	16Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31E105KA01	1 uF	25Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R11A105KA01	1 uF	10Vdc	R (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R11C105KA01	1 uF	16Vdc	R (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61A105KA01	1 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61C105KA01	1 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61E105KA01	1 uF	25Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71A105KA01	1 uF	10Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R71C105KA01	1 uF	16Vdc	X7R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR72A105KA01	1 uF	100Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11C105KA01	1 uF	16Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11E105KA01	1 uF	25Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB31H105KA87	1 uF	50Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11C105KA01	1 uF	16Vdc	R (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11E105KA01	1 uF	25Vdc	R (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR61C105KA01	1 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71C105KA01	1 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71C105MA01	1 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR71E105KA01	1 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71E105MC01	1 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR71H105KA88	1 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM316B31C225KA87	2.2 uF	16Vdc	B (JIS)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM316B31E225KA75	2.2 uF	25Vdc	B (JIS)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM316C81C225KA12	2.2 uF	16Vdc	X6S (EIA)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM316D71C225KA12	2.2 uF	16Vdc	X7T (EIA)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM316D71C225MA12	2.2 uF	16Vdc	X7T (EIA)	1206 (3216M)	0.7	±20%	General Purpose	100 Hz - 6 GHz
GRM316R61C225KA88	2.2 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM316R61E225KA12	2.2 uF	25Vdc	X5R (EIA)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11A225KA01	2.2 uF	10Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31H225KA12	2.2 uF	50Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31H225MA12	2.2 uF	50Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM319C8YA225KA12	2.2 uF	35Vdc	X6S (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61A225KA01	2.2 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61H225KA12	2.2 uF	50Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61H225MA12	2.2 uF	50Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz - 6 GHz
GRM31CB31H225KA87	2.2 uF	50Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CB31H225MA87	2.2 uF	50Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CL8EL225KE07	2.2 uF	100Vdc	X8L (MURATA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR61H225KA88	2.2 uF	50Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR71H225KA88	2.2 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR72A225KA73	2.2 uF	100Vdc	X7R (EIA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR72A225MA73	2.2 uF	100Vdc	X7R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31MB11A225KA01	2.2 uF	10Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11C225KA35	2.2 uF	16Vdc	B (JIS)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MB11C225MA35	2.2 uF	16Vdc	B (JIS)	1206 (3216M)	1.3	±20%	General Purpose	100 Hz - 6 GHz
GRM31MB31E225KA92	2.2 uF	25Vdc	B (JIS)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11A225KA01	2.2 uF	10Vdc	R (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11C225KA35	2.2 uF	16Vdc	R (JIS)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR11C225MA35	2.2 uF	16Vdc	R (JIS)	1206 (3216M)	1.3	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR11E225KA93	2.2 uF	25Vdc	R (JIS)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR61A225KA01	2.2 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR61C225KA35	2.2 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71A225KA01	2.2 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71C225KA35	2.2 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM31MR71C225MA35	2.2 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.3	±20%	General Purpose	100 Hz - 6 GHz
GRM31MR71E225KA93	2.2 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.3	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31C335KA75	3.3 uF	16Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319R61C335KA12	3.3 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR61E335KA88	3.3 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM316B31A475KE18	4.7 uF	10Vdc	B (JIS)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM316R61A475KE19	4.7 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.7	±10%	General Purpose	100 Hz - 6 GHz
GRM319B11A475KA01	4.7 uF	10Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31C475KA87	4.7 uF	16Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31E475KA75	4.7 uF	25Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz - 6 GHz
GRM319B31H475KA12	4.7 uF	50Vdc	B (JIS)	1206 (3216M)	0.95	±10%		

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM319B31H475MA12	4.7 uF	50Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319C81C475KA12	4.7 uF	16Vdc	X6S (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319D71C475KA12	4.7 uF	16Vdc	X7E (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319D71C475MA12	4.7 uF	16Vdc	X7E (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R61A475KA01	4.7 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61C475KA88	4.7 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61E475KA12	4.7 uF	25Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61H475KA12	4.7 uF	50Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61H475MA12	4.7 uF	50Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CB10J475KA01	4.7 uF	6.3Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB11A475KA01	4.7 uF	10Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB11C475KA01	4.7 uF	16Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31E475KA87	4.7 uF	25Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31H475KA12	4.7 uF	50Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31H475MA12	4.7 uF	50Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CC72A475KE11	4.7 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CC72A475ME11	4.7 uF	100Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR11C475KA01	4.7 uF	16Vdc	R (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR11C475MA01	4.7 uF	16Vdc	R (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR60J475KA01	4.7 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61A475KA01	4.7 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61C475KA01	4.7 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61C475MA01	4.7 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61E475KA88	4.7 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71A475KA01	4.7 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71C475KA01	4.7 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71C475MA01	4.7 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71E475KA88	4.7 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71H475KA12	4.7 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71H475MA12	4.7 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CZ72A475KE11	4.7 uF	100Vdc	X7R (MURATA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CZ72A475ME11	4.7 uF	100Vdc	X7R (MURATA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81C685KA12	6.8 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81C685MA12	6.8 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319B30J106KE18	10 uF	6.3Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319B31A106KE18	10 uF	10Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319B31A106ME18	10 uF	10Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319B31C106KE15	10 uF	16Vdc	B (JIS)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319B31C106ME15	10 uF	16Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319C80J106KE19	10 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319C80J106ME19	10 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319C81A106KA12	10 uF	10Vdc	X6S (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319C81A106MA12	10 uF	10Vdc	X6S (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319C81C106KA12	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319C81C106MA12	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R60J106KE19	10 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61A106KE19	10 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61A106ME19	10 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R61C106KE15	10 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61C106ME15	10 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R61E106KA12	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61E106MA12	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R6YA106KA12	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R6YA106MA12	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31C106KA88	10 uF	16Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31E106KA75	10 uF	25Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31E106MA75	10 uF	25Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31H106KA12	10 uF	50Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31H106MA12	10 uF	50Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CB3YA106KA12	10 uF	35Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB3YA106MA12	10 uF	35Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CC81C106KA12	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CC81C106KE19	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CC81C106MA12	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CC81E106KA12	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CC81E106KE15	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CC81E106MA12	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CC8YA106KA12	10 uF	35Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CC8YA106MA12	10 uF	35Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CD71H106KE11	10 uF	50Vdc	X7T (EIA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CD7YA106KE11	10 uF	35Vdc	X7T (EIA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR11A106KA01	10 uF	10Vdc	R (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR11A106MA01	10 uF	10Vdc	R (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR60J106KA01	10 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR60J106MC01	10 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61A106KA01	10 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61C106KA88	10 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61C106KC31	10 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61E106KA12	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61E106MA12	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61H106KA12	10 uF	50Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR61H106MA12	10 uF	50Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR6YA106KA12	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR6YA106MA12	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR70J106KA01	10 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71A106KA01	10 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71A106MA01	10 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71C106KA12	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71C106KAC7	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71C106MA12	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71C106MAC7	10 uF	16Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71E106KA12	10 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CR71E106MA12	10 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31MB30J106KE18	10 uF	6.3Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MB31A106KE18	10 uF	10Vdc	B (JIS)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MB31A106ME18	10 uF	10Vdc	B (JIS)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81A106KE19	10 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81A106ME19	10 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81C106KA12	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81E106KA12	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MC81E106MA12	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31MR61A106KE19	10 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MR61C106KA12	10 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MR61E106KA12	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31MR61E106MA12	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.25	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319B30J226ME15	22 uF	6.3Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319B31A226ME15	22 uF	10Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319B31C226ME15	22 uF	16Vdc	B (JIS)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319C80J226ME15	22 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R60J226ME15	22 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R61A226ME15	22 uF	10Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM319R61C226KE15	22 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	General Purpose	100 Hz ~ 6 GHz
GRM319R61C226ME15	22 uF	16Vdc	X5R (EIA)	1206 (3216M)	0.95	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CB30J226KE18	22 uF	6.3Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB30J226ME18	22 uF	6.3Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31A226KE19	22 uF	10Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz ~ 6 GHz
GRM31CB31A226ME19	22 uF	10Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz ~ 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM31CB31C226KE15	22 uF	16Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CB31C226ME15	22 uF	16Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CB31E226KE15	22 uF	25Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CB31E226ME15	22 uF	25Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC71C226KE11	22 uF	16Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC71E226ME15	22 uF	25Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC80G226KE19	22 uF	4Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CC80G226ME19	22 uF	4Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC80J226KE19	22 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CC80J226ME19	22 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC81A226KE19	22 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CC81A226ME19	22 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC81C226KE15	22 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CC81C226ME15	22 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC81E226KE11	22 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz - 6 GHz
GRM31CC81E226ME11	22 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CD70J226KE19	22 uF	6.3Vdc	X7T (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CD70J226ME19	22 uF	6.3Vdc	X7T (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CD71A226KE15	22 uF	10Vdc	X7T (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CD71A226ME15	22 uF	10Vdc	X7T (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60J226KE19	22 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR60J226ME19	22 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR61A226KE19	22 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR61A226ME19	22 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR61C226KE15	22 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR61C226ME15	22 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR61E226KE15	22 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR61E226ME15	22 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR70J226KE19	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR70J226ME19	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR71A226KE15	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR71A226ME15	22 uF	10Vdc	X7R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CZ71C226ME15	22 uF	16Vdc	X7R (MURATA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CB30J476KE18	47 uF	6.3Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CB30J476ME18	47 uF	6.3Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CB31A476KE15	47 uF	10Vdc	B (JIS)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CB31A476ME15	47 uF	10Vdc	B (JIS)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC81A476ME44	47 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CD80G476ME19	47 uF	4Vdc	X6T (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CE70G476ME15	47 uF	4Vdc	X7U (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CE70J476ME15	47 uF	6.3Vdc	X7U (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60J476KE19	47 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR60J476ME19	47 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR61A476KE15	47 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR61A476ME15	47 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR61C476ME44	47 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CD80G107MEA8	100 uF	4Vdc	X6T (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CD80J107MEA8	100 uF	6.3Vdc	X6T (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CE70G107MEA8	100 uF	4Vdc	X7U (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60G107MEA8	100 uF	4Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60J107KEA8	100 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.9	±10%	General Purpose	100 Hz - 6 GHz
GRM31CR60J107MEA8	100 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR61A107MEA8	100 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC80E227ME11	220 uF	2.5Vdc	X6S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CC80G227ME11	220 uF	4Vdc	X6S (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60E227ME11	220 uF	2.5Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60G227ME11	220 uF	4Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM31CR60J227ME11	220 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.9	±20%	General Purpose	100 Hz - 6 GHz
GRM32MR71H104KA01	100000 pF	50Vdc	X7R (EIA)	1210 (3225M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM32NR72A104KA01	100000 pF	100Vdc	X7R (EIA)	1210 (3225M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM32NR71H154KA01	150000 pF	50Vdc	X7R (EIA)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32MB11H474KA01	470000 pF	50Vdc	B (JIS)	1210 (3225M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM32MB11H474MA01	470000 pF	50Vdc	B (JIS)	1210 (3225M)	1.25	±20%	General Purpose	100 Hz - 6 GHz
GRM32CR72A684KA01	680000 pF	100Vdc	X7R (EIA)	1210 (3225M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM32NB11H684KA01	680000 pF	50Vdc	B (JIS)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32NR71H684KA01	680000 pF	50Vdc	X7R (EIA)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32CR72A105KA35	1 uF	100Vdc	X7R (EIA)	1210 (3225M)	1.8	±10%	General Purpose	100 Hz - 6 GHz
GRM32CR72A105MA35	1 uF	100Vdc	X7R (EIA)	1210 (3225M)	1.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32RB11H105KA01	1 uF	50Vdc	B (JIS)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR11H105KA01	1 uF	50Vdc	R (JIS)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR71H105KA01	1 uF	50Vdc	X7R (EIA)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER72A225KA35	2.2 uF	100Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER72A225MA35	2.2 uF	100Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32MB11C225KA01	2.2 uF	16Vdc	B (JIS)	1210 (3225M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM32MR11C225KA01	2.2 uF	16Vdc	R (JIS)	1210 (3225M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM32MR71C225KA01	2.2 uF	16Vdc	X7R (EIA)	1210 (3225M)	1.25	±10%	General Purpose	100 Hz - 6 GHz
GRM32RB11E225KA01	2.2 uF	25Vdc	B (JIS)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR71E225KA01	2.2 uF	25Vdc	X7R (EIA)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DB11E475KA61	4.7 uF	25Vdc	B (JIS)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DC72A475KE01	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DC72A475ME01	4.7 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.2	±20%	General Purpose	100 Hz - 6 GHz
GRM32DL8E1475KE07	4.7 uF	100Vdc	X8L (MURATA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR11E475KA61	4.7 uF	25Vdc	R (JIS)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR71E475KA61	4.7 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB31H475KA87	4.7 uF	50Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71H475KA88	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71K475KE14	4.7 uF	80Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71K475ME14	4.7 uF	80Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32RB11C475KA01	4.7 uF	16Vdc	B (JIS)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR11C475KA01	4.7 uF	16Vdc	R (JIS)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR61C475KA01	4.7 uF	16Vdc	X5R (EIA)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR61E475KA12	4.7 uF	25Vdc	X5R (EIA)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32RR71C475KA01	4.7 uF	16Vdc	X7R (EIA)	1210 (3225M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM32AB31C106KAB6	10 uF	16Vdc	B (JIS)	1210 (3225M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM32AR61C106KAB7	10 uF	16Vdc	X5R (EIA)	1210 (3225M)	1	±10%	General Purpose	100 Hz - 6 GHz
GRM32DB11C106KA01	10 uF	16Vdc	B (JIS)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DB31E106KA75	10 uF	25Vdc	B (JIS)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DC81E106KA12	10 uF	25Vdc	X6S (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR11C106KA01	10 uF	16Vdc	R (JIS)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR61C106KA01	10 uF	16Vdc	X5R (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR61E106KA12	10 uF	25Vdc	X5R (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR61E106MA12	10 uF	25Vdc	X5R (EIA)	1210 (3225M)	2.2	±20%	General Purpose	100 Hz - 6 GHz
GRM32DR71A106KA01	10 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR71C106KA01	10 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32DR71E106KA12	10 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB11A106KA01	10 uF	10Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB31H106KA12	10 uF	50Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB31H106MA12	10 uF	50Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB3YA106KA12	10 uF	35Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB3YA106MA12	10 uF	35Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC72A106KE05	10 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EC72A106ME05	10 uF	100Vdc	X7S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER61A106KA01	10 uF	10Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER61H106KA12	10 uF	50Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER61H106MA12	10 uF	50Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER6YA106KA12	10 uF	35Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER6YA106MA12	10 uF	35Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRM32ER71J106KA12	10 uF	63Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71J106MA12	10 uF	63Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER7YA106KA12	10 uF	35Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER7YA106MA12	10 uF	35Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32DR60J226MA01	22 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.2	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB31C226ME16	22 uF	16Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB31E226KE15	22 uF	25Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB31E226ME15	22 uF	25Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC81E226KE15	22 uF	25Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EC81E226ME15	22 uF	25Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER11A226ME20	22 uF	10Vdc	R (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER61C226ME20	22 uF	16Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER61E226KE15	22 uF	25Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER61E226ME15	22 uF	25Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER71A226ME20	22 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER71C226KEA8	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71C226MEA8	22 uF	16Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER71E226KE15	22 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71E226ME15	22 uF	25Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32NB31A226KE19	22 uF	10Vdc	B (JIS)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32NB31A226ME19	22 uF	10Vdc	B (JIS)	1210 (3225M)	1.5	±20%	General Purpose	100 Hz - 6 GHz
GRM32NC81A226ME19	22 uF	10Vdc	X6S (EIA)	1210 (3225M)	1.5	±20%	General Purpose	100 Hz - 6 GHz
GRM32NC81C226KE15	22 uF	16Vdc	X6S (EIA)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32NC81C226ME15	22 uF	16Vdc	X6S (EIA)	1210 (3225M)	1.5	±20%	General Purpose	100 Hz - 6 GHz
GRM32ND70J226ME19	22 uF	6.3Vdc	X7T (EIA)	1210 (3225M)	1.5	±20%	General Purpose	100 Hz - 6 GHz
GRM32ND71A226KE15	22 uF	10Vdc	X7T (EIA)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32ND71A226ME15	22 uF	10Vdc	X7T (EIA)	1210 (3225M)	1.5	±20%	General Purpose	100 Hz - 6 GHz
GRM32NR61A226KE19	22 uF	10Vdc	X5R (EIA)	1210 (3225M)	1.5	±10%	General Purpose	100 Hz - 6 GHz
GRM32NR61A226ME19	22 uF	10Vdc	X5R (EIA)	1210 (3225M)	1.5	±20%	General Purpose	100 Hz - 6 GHz
GRM32DR60J336ME19	33 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.2	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB30J476ME16	47 uF	6.3Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB31A476KE20	47 uF	10Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB31A476ME20	47 uF	10Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB31C476KE15	47 uF	16Vdc	B (JIS)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EB31C476ME15	47 uF	16Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80J476KE64	47 uF	6.3Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EC80J476ME64	47 uF	6.3Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC81A476KE19	47 uF	10Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EC81A476ME19	47 uF	10Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC81C476KE15	47 uF	16Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EC81C476ME15	47 uF	16Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ED70J476KE20	47 uF	6.3Vdc	X7T (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ED70J476ME20	47 uF	6.3Vdc	X7T (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ED71A476KE15	47 uF	10Vdc	X7T (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ED71A476ME15	47 uF	10Vdc	X7T (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EE70J476KE20	47 uF	6.3Vdc	X7U (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EE70J476ME20	47 uF	6.3Vdc	X7U (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60J476KE64	47 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER60J476ME20	47 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60J476ME64	47 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER61A476KE20	47 uF	10Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER61A476ME20	47 uF	10Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER61C476KE15	47 uF	16Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER61C476ME15	47 uF	16Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER70J476KE20	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER70J476ME20	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER71A476KE15	47 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32ER71A476ME15	47 uF	10Vdc	X7R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EB30J107ME16	100 uF	6.3Vdc	B (JIS)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC70G107ME15	100 uF	4Vdc	X7S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC70J107ME15	100 uF	6.3Vdc	X7S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80G107KE20	100 uF	4Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM32EC80G107ME20	100 uF	4Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80J107ME20	100 uF	6.3Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EE70G107ME19	100 uF	4Vdc	X7U (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EE70J107ME15	100 uF	6.3Vdc	X7U (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60J107ME20	100 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER61A107ME20	100 uF	10Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80E227ME05	220 uF	2.5Vdc	X6S (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80G227ME05	220 uF	4Vdc	X6S (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80J227ME01	220 uF	6.3Vdc	X6S (EIA)	1210 (3225M)	2.85	±20%	General Purpose	100 Hz - 6 GHz
GRM32ED70E227ME01	220 uF	2.5Vdc	X7T (EIA)	1210 (3225M)	2.85	±20%	General Purpose	100 Hz - 6 GHz
GRM32ED70G227ME01	220 uF	4Vdc	X7T (EIA)	1210 (3225M)	2.85	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60G227ME05	220 uF	4Vdc	X5R (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60J227ME05	220 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32EC80E337ME05	330 uF	2.5Vdc	X6S (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60E337ME05	330 uF	2.5Vdc	X5R (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM32ER60G337ME05	330 uF	4Vdc	X5R (EIA)	1210 (3225M)	2.8	±20%	General Purpose	100 Hz - 6 GHz
GRM43ER11H225KA01	2.2 uF	50Vdc	R (JIS)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43ER71H225KA01	2.2 uF	50Vdc	X7R (EIA)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43ER72A225KA01	2.2 uF	100Vdc	X7R (EIA)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43EB31H475KA88	4.7 uF	50Vdc	B (JIS)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43ER11E475KA01	4.7 uF	25Vdc	R (JIS)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43ER61H475KA88	4.7 uF	50Vdc	X5R (EIA)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43ER71E475KA01	4.7 uF	25Vdc	X7R (EIA)	1812 (4532M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM43DR61E106KA12	10 uF	25Vdc	X5R (EIA)	1812 (4532M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM43EB11C226ME01	22 uF	16Vdc	B (JIS)	1812 (4532M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM43ER61C226ME01	22 uF	16Vdc	X5R (EIA)	1812 (4532M)	2.7	±20%	General Purpose	100 Hz - 6 GHz
GRM55DR72A105KA01	1 uF	100Vdc	X7R (EIA)	2220 (5750M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM55RB11H105KA01	1 uF	50Vdc	B (JIS)	2220 (5750M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM55RR11H105KA01	1 uF	50Vdc	R (JIS)	2220 (5750M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM55RR71H105KA01	1 uF	50Vdc	X7R (EIA)	2220 (5750M)	2	±10%	General Purpose	100 Hz - 6 GHz
GRM55EB11H475KA01	4.7 uF	50Vdc	B (JIS)	2220 (5750M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM55ER11H475KA01	4.7 uF	50Vdc	R (JIS)	2220 (5750M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM55ER61H475KA01	4.7 uF	50Vdc	X5R (EIA)	2220 (5750M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM55ER71H475KA01	4.7 uF	50Vdc	X7R (EIA)	2220 (5750M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM55ER72A475KA01	4.7 uF	100Vdc	X7R (EIA)	2220 (5750M)	2.7	±10%	General Purpose	100 Hz - 6 GHz
GRM55DB11E106KA01	10 uF	25Vdc	B (JIS)	2220 (5750M)	2.1	±10%	General Purpose	100 Hz - 6 GHz
GRM55DB31H106KA87	10 uF	50Vdc	B (JIS)	2220 (5750M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM55DR11E106KA01	10 uF	25Vdc	R (JIS)	2220 (5750M)	2.1	±10%	General Purpose	100 Hz - 6 GHz
GRM55DR61H106KA88	10 uF	50Vdc	X5R (EIA)	2220 (5750M)	2.2	±10%	General Purpose	100 Hz - 6 GHz
GRM55DR71E106KA01	10 uF	25Vdc	X7R (EIA)	2220 (5750M)	2.1	±10%	General Purpose	100 Hz - 6 GHz
GRM55DR76E106ME05	20 uF	16Vdc	X5R (EIA)	0704 (1810M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM55DR76E106ME05	22 uF	16Vdc	X5R (EIA)	0704 (1810M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM55DR76E106ME05	43 uF	6.3Vdc	X5R (EIA)	0704 (1810M)	0.8	±20%	General Purpose	100 Hz - 6 GHz
GRM55DR76E106ME05	1 uF	6.3Vdc	X5R (EIA)	015008 (05025M)	0.275	±20%	Ultra-small	100 Hz - 6 GHz
GRM55DR76E106ME05	100 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	150 pF	25Vdc	X6S (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	150 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	220 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	220 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	330 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	470 pF	25Vdc	X6S (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	470 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	470 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	680 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz - 6 GHz
GRM55DR76E106ME05	1000 pF	25Vdc	X6S (EIA)	0201 (0603M)	0.33	±10%	Infotainment for Automotive [AEC-Q200]	100 Hz -

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRT033R61E102KE01	1000 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R71E102KE01	1000 pF	25Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A152KE01	1500 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J222KE01	2200 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A222KE01	2200 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R70J222KE01	2200 pF	6.3Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J332KE01	3300 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A332KE01	3300 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R70J332KE01	3300 pF	6.3Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J472KE01	4700 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A472KE01	4700 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61E472KE01	4700 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R70J472KE01	4700 pF	6.3Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J682KE01	6800 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A682KE01	6800 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61E682KE01	6800 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R70J682KE01	6800 pF	6.3Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J103KE01	10000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J103KE01	10000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A103KE01	10000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C103KE01	10000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61E103KE01	10000 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R70J103KE01	10000 pF	6.3Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R71A103KE01	10000 pF	10Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R71C103KE01	10000 pF	16Vdc	X7R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J153KE01	15000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J153KE01	15000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A153KE01	15000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C153KE01	15000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J223KE01	22000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J223KE01	22000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A223KE01	22000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C223KE01	22000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J333KE01	33000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J333KE01	33000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A333KE01	33000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C333KE01	33000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J473KE01	47000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J473KE01	47000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A473KE01	47000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C473KE01	47000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J683KE01	68000 pF	4Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J683KE01	68000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J683KE01	68000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A683KE01	68000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C683KE01	68000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J823KE01	82000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C70J104KE01	100000 pF	6.3Vdc	X7S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C71A104KE01	100000 pF	10Vdc	X7S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C71C104KE01	100000 pF	16Vdc	X7S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80G104KE01	100000 pF	4Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J104KE01	100000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C81A104KE01	100000 pF	10Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C81C104KE01	100000 pF	16Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C81E104KE01	100000 pF	25Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J104KE01	100000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A104KE01	100000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61C104KE01	100000 pF	16Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61E104KE01	100000 pF	25Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R6YA104KE01	100000 pF	35Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80G224ME01	220000 pF	4Vdc	X6S (EIA)	0201 (0603M)	0.33	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J224KE01	220000 pF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J224KE01	220000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R61A224KE01	220000 pF	10Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J334ME01	330000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J474KE01	470000 pF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.33	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C80J105ME13	1 uF	6.3Vdc	X6S (EIA)	0201 (0603M)	0.39	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033C81A105ME13	1 uF	10Vdc	X6S (EIA)	0201 (0603M)	0.39	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033D70E105ME18	1 uF	2.5Vdc	X7T (EIA)	0201 (0603M)	0.39	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033D70G105ME13	1 uF	4Vdc	X7T (EIA)	0201 (0603M)	0.39	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033D70J105ME13	1 uF	6.3Vdc	X7T (EIA)	0201 (0603M)	0.39	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60G105ME13	1 uF	4Vdc	X5R (EIA)	0201 (0603M)	0.35	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT033R60J105ME13	1 uF	6.3Vdc	X5R (EIA)	0201 (0603M)	0.35	± 20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H221KE01	220 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H217KE01	270 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H331KE01	330 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H471KE01	470 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H681KE01	680 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H821KE01	820 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H102KE01	1000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H152KE01	1500 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H222KE01	2200 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H272KE01	2700 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H332KE01	3300 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H472KE01	4700 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71E562KE01	5600 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H682KE01	6800 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C103KE01	10000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71E103KE01	10000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H103KE01	10000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 kHz - 6 GHz
GRT155R71H153KE01	15000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R70J223KE01	22000 pF	6.3Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C223KE01	22000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71E223KE01	22000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H223KE01	22000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C333KE01	33000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71E333KE01	33000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H333KE01	33000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H393KE01	39000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C473KE01	47000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71E473KE01	47000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H473KE01	47000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H563KE01	56000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C683KE01	68000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H683KE01	68000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71H823KE01	82000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	± 10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C104KE01								

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRT155R61C224KE01	220000 pF	16Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61E224KE01	220000 pF	25Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R6YA224KE01	220000 pF	35Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71A224KE01	220000 pF	10Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71C224KE01	220000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J334KE01	330000 pF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J334KE01	330000 pF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A334KE01	330000 pF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J474KE01	470000 pF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81C474KE01	470000 pF	16Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J474KE01	470000 pF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A474KE01	470000 pF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61C474KE01	470000 pF	16Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61E474KE01	470000 pF	25Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R6YA474KE01	470000 pF	35Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R71A474KE01	470000 pF	10Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J684KE01	680000 pF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J684KE01	680000 pF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A684KE01	680000 pF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT153R60J105ME13	1 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.33	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT153R61A105ME13	1 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.33	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C71A105KE13	1 uF	10Vdc	X7S (EIA)	0402 (1005M)	0.6	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J105KE01	1 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81A105KE01	1 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81C105KE13	1 uF	16Vdc	X6S (EIA)	0402 (1005M)	0.6	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81E105KE13	1 uF	25Vdc	X6S (EIA)	0402 (1005M)	0.6	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J105KE01	1 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A105KE01	1 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61C105KE01	1 uF	16Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61E105KE01	1 uF	25Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R6YA105KE13	1 uF	35Vdc	X5R (EIA)	0402 (1005M)	0.6	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R70G105KE01	1 uF	4Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R70J105KE01	1 uF	6.3Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT153R60J225ME13	2.2 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.33	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C70J225KE13	2.2 uF	6.3Vdc	X7S (EIA)	0402 (1005M)	0.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C71A225KE13	2.2 uF	10Vdc	X7S (EIA)	0402 (1005M)	0.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80G225KE13	2.2 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J225KE01	2.2 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81A225KE13	2.2 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81C225KE13	2.2 uF	16Vdc	X6S (EIA)	0402 (1005M)	0.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J225KE01	2.2 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A225KE01	2.2 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61C225KE13	2.2 uF	16Vdc	X5R (EIA)	0402 (1005M)	0.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61E225KE13	2.2 uF	25Vdc	X5R (EIA)	0402 (1005M)	0.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R6YA225ME13	4.7 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.65	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J475ME13	4.7 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.65	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C81A475ME13	4.7 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J475ME13	4.7 uF	6.3Vdc	X7T (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60G475ME13	4.7 uF	4Vdc	X5R (EIA)	0402 (1005M)	0.6	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J475ME13	4.7 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.6	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A475ME13	4.7 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80E106ME13	10 uF	2.5Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80G106ME13	10 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155C80J106ME13	10 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155D70G106ME13	10 uF	4Vdc	X7T (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R60J106ME13	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT155R61A106ME13	10 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R72A332KE01	3300 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R72A103KE01	10000 pF	100Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71H473KE01	47000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71H104KE13	100000 pF	50Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71E154KE01	150000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71E224KE01	220000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71C334KE01	330000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71C474KE01	470000 pF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71E474KE13	470000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C80G105ME01	1 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81A105KE13	1 uF	10Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81C105KE13	1 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81E105KE13	1 uF	25Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C8YA105KE13	1 uF	35Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R60J105KE01	1 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R60J105ME01	1 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61A105KE01	1 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61A105ME01	1 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61C105KE13	1 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61E105KE13	1 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61H105KE13	1 uF	50Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R6YA105KE13	1 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71C105KE13	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R71E105KE13	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C71C225KE13	2.2 uF	16Vdc	X7S (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C71E225KE13	2.2 uF	25Vdc	X7S (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81C225KE13	2.2 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81E225KE13	2.2 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C8YA225KE13	2.2 uF	35Vdc	X6S (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R60J225KE13	2.2 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61A225KE13	2.2 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61E225KE13	2.2 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61H225KE13	2.2 uF	50Vdc	X5R (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R6YA225KE13	2.2 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R70J225KE13	2.2 uF	6.3Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C71C475KE13	4.7 uF	16Vdc	X7S (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C80G475KE01	4.7 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C80J475KE01	4.7 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C80J475ME01	4.7 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81C475KE13	4.7 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81E475KE13	4.7 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R60J475KE01	4.7 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61C475KE13	4.7 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R61E475KE13	4.7 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R6YA475KE13	4.7 uF	35Vdc	X5R (EIA)	0603 (1608M)	1	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C80G106ME13	10 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C80J106ME13	10 uF	6.3Vdc	X6S (EIA)	0603 (1608M)	1	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81A106ME13	10 uF	10Vdc	X6S (EIA)	0603 (1608M)	1	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188C81C106ME13	10 uF	16Vdc	X6S (EIA)	0603 (1608M)	1	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188D70J106ME13	10 uF	6.3Vdc	X7T (EIA)	0603 (1608M)	1	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188D71A106ME13	10 uF	10Vdc	X7T (EIA)	0603 (1608M)	1	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R60G106ME13	10 uF	4Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT188R60J106ME13	10 uF	6.3Vdc	X5R (EIA)	0				

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (Simulation model)
GRT18BR61A228ME13	22 uF	10Vdc	X5R (EIA)	0603 (1608M)	1	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR72A473KE01	47000 pF	100Vdc	X7R (EIA)	0805 (2012M)	1.35	±1%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71H474KE01	470000 pF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81E105KE13	1 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71E105KE13	1 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71H105KE01	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81C225KA02	2.2 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81E225KA02	2.2 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC8YA225KE13	2.2 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BD71H225KE13	2.2 uF	50Vdc	X7T (EIA)	0805 (2012M)	1.45	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BD72A225KE13	2.2 uF	100Vdc	X7T (EIA)	0805 (2012M)	1.45	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61C225KA02	2.2 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61E225KA02	2.2 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61H225KE13	2.2 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71C225KE01	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71E225KE13	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21R961A335KE01	3.3 uF	10Vdc	X5R (EIA)	0805 (2012M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21R961C335KE01	3.3 uF	16Vdc	X5R (EIA)	0805 (2012M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81C335KE13	3.3 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81E335KE13	3.3 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61A335KE13	3.3 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT219CB1A475KE01	4.7 uF	10Vdc	X6S (EIA)	0805 (2012M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC71E475KE13	4.7 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC71H475KE13	4.7 uF	50Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81C475KA02	4.7 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81E475KA02	4.7 uF	25Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC8YA475KE13	4.7 uF	35Vdc	X6S (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR60J475KE13	4.7 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61A475KE13	4.7 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61C475KA02	4.7 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61E475KA02	4.7 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61H475KE13	4.7 uF	50Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71A475KE13	4.7 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71C475KE13	4.7 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC71C106KE13	10 uF	16Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC71E106KE13	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81A106KE01	10 uF	10Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81C106KE01	10 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR60J106KE01	10 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61A106KE01	10 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61C106KE01	10 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.35	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61E106KE13	10 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR70J106KE13	10 uF	6.3Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR71A106KE13	10 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81A226ME13	22 uF	10Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC81C226ME13	22 uF	16Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BD70J226ME13	22 uF	6.3Vdc	X7T (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BD71A226ME13	22 uF	10Vdc	X7T (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR60J226ME13	22 uF	6.3Vdc	X5R (EIA)	0805 (2012M)	1.4	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61A226ME13	22 uF	10Vdc	X5R (EIA)	0805 (2012M)	1.4	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61C226ME13	22 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BR61E226ME13	22 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC80E476ME13	47 uF	2.5Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT21BC80G476ME13	47 uF	4Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MC81H105KE01	1 uF	50Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81H155KE01	1.5 uF	50Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61H155KE01	1.5 uF	50Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MC81C155KE01	1.5 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MC81E155KE01	1.5 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MR61C155KE01	1.5 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MR61E155KE01	1.5 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81H225KE01	2.2 uF	50Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61H225KE01	2.2 uF	50Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR71H225KE13	2.2 uF	50Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61E335KE01	3.3 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81C475KE01	4.7 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81C475ME01	4.7 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81E475KE01	4.7 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61C475KE01	4.7 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61C475ME01	4.7 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61E475KE01	4.7 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MC81C685KE01	6.8 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MR61C685KE01	6.8 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31R96YA106KE01	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	0.95	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81A106KE01	10 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81A106ME01	10 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81C106KE01	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81C106ME01	10 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81E106KE01	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC8YA106KE01	10 uF	35Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CD71H106KE13	10 uF	50Vdc	X7T (EIA)	1206 (3216M)	1.9	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61A106KE01	10 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61C106KE01	10 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61E106KE01	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61E106ME01	10 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61H106KE01	10 uF	50Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR6YA106KE01	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR71E106KE13	10 uF	25Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31MC81E106KE01	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.25	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR60J156KE01	15 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC71C226ME13	22 uF	16Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC71E226ME13	22 uF	25Vdc	X7S (EIA)	1206 (3216M)	1.9	±20%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC80G226KE01	22 uF	4Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC80J226KE01	22 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81A226KE01	22 uF	10Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC81C226KE01	22 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR60J226KE01	22 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61A226KE01	22 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61C226KE01	22 uF	16Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61E226KE01	22 uF	25Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR70J226KE13	22 uF	6.3Vdc	X7R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CC80J476KE13	47 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR60J476KE13	47 uF	6.3Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT31CR61A476KE13	47 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32DC81H335KE01	3.3 uF	50Vdc	X6S (EIA)	1210 (3225M)	2.2	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32DR61H335KE01	3.3 uF	50Vdc	X5R (EIA)	1210 (3225M)	2.2	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32EC81H475KE01	4.7 uF	50Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32ER61H475KE01	4.7 uF	50Vdc	X5R (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32ER71H475KE01	4.7 uF	50Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32NR61E685KE01	6.8 uF	25Vdc	X6S (EIA)	1210 (3225M)	1.5	±10%	Infotainment for Automotive AEC-Q200	100 Hz - 6 GHz
GRT32DC81A106KE01	10 uF	10Vdc	X6S (EIA)	1210 (3225M)	2.2	±10%	Infotainment for Automotive AEC-Q200	

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code (inch (mm))	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
GRT32ER61C226ME13	22 uF	16Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32ER61E226ME13	22 uF	25Vdc	X5R (EIA)	1210 (3225M)	2.7	±1%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32DR60J336ME01	33 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.2	±20%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32EC80J478KE13	47 uF	6.3Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32EC81A478KE13	47 uF	10Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32EC81C478KE13	47 uF	16Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32EC81C478ME13	47 uF	16Vdc	X6S (EIA)	1210 (3225M)	2.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32ER70J478KE13	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32EC70G107ME13	100 uF	4Vdc	X7S (EIA)	1210 (3225M)	2.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32EC70J107ME13	100 uF	6.3Vdc	X7S (EIA)	1210 (3225M)	2.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GRT32ER60J107ME13	100 uF	6.3Vdc	X5R (EIA)	1210 (3225M)	2.7	±20%	Infotainment for Automotive AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H221KE01	220 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H471KE01	470 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H102KE01	1000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H222KE01	2200 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H472KE01	4700 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71C103KE01	10000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71E103KE01	10000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H103KE01	10000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 kHz ~ 6 GHz
GXT155R71C223KE01	22000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71E223KE01	22000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H223KE01	22000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71C473KE01	47000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71E473KE01	47000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H473KE01	47000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71E104KE01	100000 pF	25Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71H104KE01	100000 pF	50Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C80J224KE01	220000 pF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81E224KE01	220000 pF	25Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C8YA224KE01	220000 pF	35Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R60J224KE01	220000 pF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61A224KE01	220000 pF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61C224KE01	220000 pF	16Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61E224KE01	220000 pF	25Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R6YA224KE01	220000 pF	35Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71A224KE01	220000 pF	10Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71C224KE01	220000 pF	16Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C80J474KE01	470000 pF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81C474KE01	470000 pF	16Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R60J474KE01	470000 pF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61A474KE01	470000 pF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61C474KE01	470000 pF	16Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61E474KE01	470000 pF	25Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R6YA474KE01	470000 pF	35Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R71A474KE01	470000 pF	10Vdc	X7R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C71A105KE13	1 uF	10Vdc	X7S (EIA)	0402 (1005M)	0.6	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C80J105KE13	1 uF	6.3Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81A105KE13	1 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81C105KE13	1 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.6	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81E105KE13	1 uF	25Vdc	X6S (EIA)	0402 (1005M)	0.6	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R60J105KE13	1 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61A105KE13	1 uF	10Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61C105KE13	1 uF	16Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61E105KE13	1 uF	25Vdc	X5R (EIA)	0402 (1005M)	0.55	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R6YA105KE13	1 uF	35Vdc	X5R (EIA)	0402 (1005M)	0.6	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C71A225KE13	2.2 uF	10Vdc	X7S (EIA)	0402 (1005M)	0.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81A225KE13	2.2 uF	10Vdc	X6S (EIA)	0402 (1005M)	0.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155C81C225KE13	2.2 uF	16Vdc	X6S (EIA)	0402 (1005M)	0.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61C225KE13	2.2 uF	16Vdc	X5R (EIA)	0402 (1005M)	0.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT155R61E225KE13	2.2 uF	25Vdc	X5R (EIA)	0402 (1005M)	0.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R71E224KE01	220000 pF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C80G105ME01	1 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R71C105KE13	1 uF	16Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R71E105KE13	1 uF	25Vdc	X7R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C81E225KE13	2.2 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C8YA225KE13	2.2 uF	35Vdc	X6S (EIA)	0603 (1608M)	1	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R61H225KE13	2.2 uF	50Vdc	X5R (EIA)	0603 (1608M)	1	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R6YA225KE13	2.2 uF	35Vdc	X5R (EIA)	0603 (1608M)	0.9	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C81C475KE13	4.7 uF	16Vdc	X6S (EIA)	0603 (1608M)	0.95	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C81E475KE13	4.7 uF	25Vdc	X6S (EIA)	0603 (1608M)	1	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R61C475KE13	4.7 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R61E475KE13	4.7 uF	25Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R6YA475KE13	4.7 uF	35Vdc	X5R (EIA)	0603 (1608M)	1	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C80G106ME13	10 uF	4Vdc	X6S (EIA)	0603 (1608M)	0.9	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C81A106ME13	10 uF	10Vdc	X6S (EIA)	0603 (1608M)	1	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188C81C106ME13	10 uF	16Vdc	X6S (EIA)	0603 (1608M)	1	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R60G106ME13	10 uF	4Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R60J106ME13	10 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.9	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R61A106KE13	10 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R61C106KE13	10 uF	16Vdc	X5R (EIA)	0603 (1608M)	0.95	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT188R61E106ME13	10 uF	25Vdc	X5R (EIA)	0603 (1608M)	1	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BR71H105KE01	1 uF	50Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BR71C225KE01	2.2 uF	16Vdc	X7R (EIA)	0805 (2012M)	1.35	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BR71E225KE13	2.2 uF	25Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BR71A475KE13	4.7 uF	10Vdc	X7R (EIA)	0805 (2012M)	1.4	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BC71E106KE13	10 uF	25Vdc	X7S (EIA)	0805 (2012M)	1.45	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BC81A226ME13	22 uF	10Vdc	X6S (EIA)	0805 (2012M)	1.45	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BR61C226ME13	22 uF	16Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT21BR61E226ME13	22 uF	25Vdc	X5R (EIA)	0805 (2012M)	1.45	±20%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT31CC81E106KE01	10 uF	25Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT31CC8YA106KE01	10 uF	35Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT31CR6YA106KE01	10 uF	35Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT31CC81C226KE01	22 uF	16Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT31CC80J476KE13	47 uF	6.3Vdc	X6S (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT31CR61A476KE13	47 uF	10Vdc	X5R (EIA)	1206 (3216M)	1.8	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT32EC81A476KE13	47 uF	10Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT32EC81C476KE13	47 uF	16Vdc	X6S (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
GXT32ER70J476KE13	47 uF	6.3Vdc	X7R (EIA)	1210 (3225M)	2.7	±10%	Water repellent/ Infotainment AEC-Q200	100 Hz ~ 6 GHz
LLC152D70G105ME01	1 uF	4Vdc	X7T (EIA)	0204 (0510M)	0.22	±20%	ESL for Powertrain/Safety for Automotive/AEC-Q	100 Hz ~ 6 GHz
LLC15SD70E105ME01	1 uF	25Vdc	X7T (EIA)	0204 (0510M)	0.18	±20%	ESL for Powertrain/Safety for Automotive/AEC-Q	100 Hz ~ 6 GHz
LLL03TR61E333KE01	33000 pF	25Vdc	X5R (EIA)	0102 (0306M)	0.2	±10%	Low ESL	100 Hz ~ 6 GHz
LLL153C70E104ME01	100000 pF	25Vdc	X7S (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153C70G104ME01	100000 pF	4Vdc	X7S (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153C80G104ME01	100000 pF	4Vdc	X6S (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153C80J104ME01	100000 pF	6.3Vdc	X6S (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153R60G104ME01	100000 pF	4Vdc	X5R (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153R60J104ME01	100000 pF	6.3Vdc	X5R (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153R61A104ME01	100000 pF	10Vdc	X5R (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz ~ 6 GHz
LLL153C80G224ME14	220000 pF							

Part Number	Capacitance (Nominal)	Rated Voltage (V)	Temperature Characteristics	Size Code inch (mm)	T size (mm Max.)	Capacitance Tolerance	Type	Frequency Range (simulation model)
LLL153R60G474ME17	470000 pF	4Vdc	X5R (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz - 6 GHz
LLL152D70G105ME01	1 uF	4Vdc	X7T (EIA)	0204 (0510M)	0.22	±20%	Low ESL	100 Hz - 6 GHz
LLL152D70J105ME01	1 uF	6.3Vdc	X7T (EIA)	0204 (0510M)	0.22	±20%	Low ESL	100 Hz - 6 GHz
LLL153C70E105ME21	1 uF	2.5Vdc	X7S (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz - 6 GHz
LLL153C80G105ME21	1 uF	4Vdc	X6S (EIA)	0204 (0510M)	0.35	±20%	Low ESL	100 Hz - 6 GHz
LLL155D70E105ME01	1 uF	2.5Vdc	X7T (EIA)	0204 (0510M)	0.18	±20%	Low ESL	100 Hz - 6 GHz
LLL155D70G105ME01	1 uF	4Vdc	X7T (EIA)	0204 (0510M)	0.18	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71H222MA01	2200 pF	50Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71H472MA01	4700 pF	50Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71C103MA01	10000 pF	16Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71C103MA11	10000 pF	16Vdc	X7R (EIA)	0306 (0816M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71E103MA01	10000 pF	25Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71E103MA11	10000 pF	25Vdc	X7R (EIA)	0306 (0816M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71C223MA01	22000 pF	16Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71C223MA11	22000 pF	16Vdc	X7R (EIA)	0306 (0816M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71E223MA01	22000 pF	25Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71E223MA11	22000 pF	25Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71C473MA01	47000 pF	16Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71C473MA11	47000 pF	16Vdc	X7R (EIA)	0306 (0816M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71A104MA01	100000 pF	10Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71A104MA11	100000 pF	10Vdc	X7R (EIA)	0306 (0816M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL185C70G224MA11	220000 pF	4Vdc	X7S (EIA)	0306 (0816M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL185R70J224MA01	220000 pF	6.3Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R71A224MA01	220000 pF	10Vdc	X7R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185C70G474MA01	470000 pF	4Vdc	X7S (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185R60J474MA01	470000 pF	6.3Vdc	X5R (EIA)	0306 (0816M)	0.6	±20%	Low ESL	100 Hz - 6 GHz
LLL185C70G105ME01	1 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLL185C70J105ME14	1 uF	6.3Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLL185R60J105ME14	1 uF	6.3Vdc	X5R (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLL185C70G225ME01	2.2 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLL185R60J225ME14	2.2 uF	6.3Vdc	X5R (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLL185C70G475ME17	4.7 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLL1U4D80E435ME22	4.3 uF	2.5Vdc	X6T (EIA)	02404 (0610M)	0.45	±20%	Low ESL	100 Hz - 6 GHz
LLL1U4R60G435ME22	4.3 uF	4Vdc	X5R (EIA)	02404 (0610M)	0.45	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71E103MA11	10000 pF	25Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71H103MA11	10000 pF	50Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71H103MA01	10000 pF	50Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71C223MA11	22000 pF	16Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71E223MA11	22000 pF	25Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71E223MA01	22000 pF	25Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71H223MA01	22000 pF	50Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71C473MA11	47000 pF	16Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71C473MA01	47000 pF	16Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71E473MA01	47000 pF	25Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71C104MA11	100000 pF	16Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71C104MA01	100000 pF	16Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71E104MA01	100000 pF	25Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL215R71A224MA11	220000 pF	10Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL216R71A224MA01	220000 pF	10Vdc	X7R (EIA)	0508 (1220M)	0.7	±20%	Low ESL	100 Hz - 6 GHz
LLL219R71C224MA01	220000 pF	16Vdc	X7R (EIA)	0508 (1220M)	0.95	±20%	Low ESL	100 Hz - 6 GHz
LLL215R70J474MA11	470000 pF	6.3Vdc	X7R (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL219R71A474MA01	470000 pF	10Vdc	X7R (EIA)	0508 (1220M)	0.95	±20%	Low ESL	100 Hz - 6 GHz
LLL215C70G105MA11	1 uF	4Vdc	X7S (EIA)	0508 (1220M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL219R70J105MA01	1 uF	6.3Vdc	X7R (EIA)	0508 (1220M)	0.95	±20%	Low ESL	100 Hz - 6 GHz
LLL219R71A105MA01	1 uF	10Vdc	X7R (EIA)	0508 (1220M)	0.95	±20%	Low ESL	100 Hz - 6 GHz
LLL219C70G225MA01	2.2 uF	4Vdc	X7S (EIA)	0508 (1220M)	0.95	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71H103MA11	10000 pF	50Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71H103MA01	10000 pF	50Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71C223MA11	22000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71E223MA11	22000 pF	25Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71H223MA11	22000 pF	50Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71E223MA01	22000 pF	25Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71H223MA01	22000 pF	50Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71C473MA11	47000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71E473MA11	47000 pF	25Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71E473MA01	47000 pF	25Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71H473MA01	47000 pF	50Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71C104MA11	100000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71E104MA11	100000 pF	25Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71C104MA01	100000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71E104MA01	100000 pF	25Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71E104MA01	100000 pF	25Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71H104MA01	100000 pF	50Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71C224MA11	220000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71C224MA01	220000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71E224MA01	220000 pF	25Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL315R71A474MA11	470000 pF	10Vdc	X7R (EIA)	0612 (1632M)	0.5	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71A474MA01	470000 pF	10Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71C474MA01	470000 pF	16Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71C474MA01	470000 pF	16Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71E474MA01	470000 pF	25Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL317R71A105MA01	1 uF	10Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71C105MA01	1 uF	16Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL317R70J225MA01	2.2 uF	6.3Vdc	X7R (EIA)	0612 (1632M)	0.8	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR71A225MA01	2.2 uF	10Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR70J475MA01	4.7 uF	6.3Vdc	X7R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLL31MR60J106ME01	10 uF	6.3Vdc	X5R (EIA)	0612 (1632M)	1.25	±20%	Low ESL	100 Hz - 6 GHz
LLR185C70G105ME01	1 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLR185C70G105ME03	1 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLR185C70G105ME05	1 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
LLR185C70G105ME07	1 uF	4Vdc	X7S (EIA)	0306 (0816M)	0.55	±20%	Low ESL	100 Hz - 6 GHz
ZRA21CR61E226ME01	22 uF	25Vdc	X5R (EIA)	0402 (1005M)	1.65	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB155R61E225ME01	2.2 uF	25Vdc	X5R (EIA)	0402 (1005M)	0.65	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB157R61E225KE11	2.2 uF	25Vdc	X5R (EIA)	0402 (1005M)	0.85	±10%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB157R6Y A225KE11	2.2 uF	35Vdc	X5R (EIA)	0402 (1005M)	0.85	±10%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB157R6Y A225ME11	2.2 uF	35Vdc	X5R (EIA)	0402 (1005M)	0.85	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB15XC80G106ME05	10 uF	4Vdc	X6S (EIA)	0402 (1005M)	0.85	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB15XR60J106ME12	10 uF	6.3Vdc	X5R (EIA)	0402 (1005M)	0.8	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AR6Y A475KE05	4.7 uF	35Vdc	X5R (EIA)	0603 (1608M)	1.2	±10%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AR6Y A475ME05	4.7 uF	35Vdc	X5R (EIA)	0603 (1608M)	1.2	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AR61E106KE01	10 uF	25Vdc	X5R (EIA)	0603 (1608M)	1.2	±10%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AR61E106ME01	10 uF	25Vdc	X5R (EIA)	0603 (1608M)	1.2	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB186R60G226ME11	22 uF	4Vdc	X5R (EIA)	0603 (1608M)	0.8	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB186R60J226ME11	22 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	0.8	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18R61A226ME05	22 uF	10Vdc	X5R (EIA)	0603 (1608M)	0.95	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AR61A226ME01	22 uF	10Vdc	X5R (EIA)	0603 (1608M)	1.2	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AC80E476ME01	47 uF	2.5Vdc	X6S (EIA)	0603 (1608M)	1.2	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz
ZRB18AR60J476ME01	47 uF	6.3Vdc	X5R (EIA)	0603 (1608M)	1.2	±20%	Acoustic noise reduction (interposer)	100 Hz - 6 GHz