

Product Search Data Sheet

NFZ2MSD600SN10#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of NFZ2MSD600SN10# from the official website of Murata

http://www.murata.com/en-sg/products/productdetail?partno=NFZ2MSD600SN10%23

"#"at the end indicates the package specification code.

In Production RoHS REACH

< List of part numbers with package codes > NFZ2MSD600SN10L




Applications

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
	Consumer equipment,Medical
	equipment [GHTF A/B/C] except for
	implant & surgery & auto injector,
	Industrial equipment except for
	transportation & facility & energy
	equipment
Specific	Please refer to Our Website and
Applications	specifications, etc. for information about
	the performance, functions, quality,
	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.
Recommended	O
Applications	Consumer equipment



Appearance & Shape





(in mm)



Packaging	Specifications	Standard Packing Quantity
L	180mm Embossed Tape	3000



1. NFZ2MSD_SN is a noise filter designed for noise

suppression of audio lines such as PC and AVequipment. 2. Can be used in high current circuits due to its low DC resistance.

- 3. Low magnetic flux leakage with magnetically shielded structure.
- 4. Meets 125°C maximum operating temperature.

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





NFZ2MSD600SN10#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

 $\label{eq:please} Please \ download \ the \ latest \ data sheet \ of \ NFZ2MSD600SN10\# \ from \ the \ of \ ficial \ website \ of \ Murata$

http://www.murata.com/en-sg/products/productdetail?partno=NFZ2MSD600SN10%23

"#"at the end indicates the package specification code.



Specifications

Shape	SMD
Size Code (in inch)	0806
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.6mm
Width Tolerance	±0.2mm
Thickness	1.2mm
Thickness Tolerance	max.
Operating Temperature Range	-40°C to 85°C
Operating Temperature Range (Self-temperature rise is included)	-40℃ to 125℃
Mass(typ.)	0.0188g
Number of Circuit	1
Rated Current (at 85°C)	2.7A
DC Resistance(max.)	54mΩ
DC Resistance	54mΩ max.
Impedance (at 10MHz)	60Ω
Impedance (at 10MHz) Tolerance	±30%
Size Code (in mm)	2016

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Product Search Data Sheet



NFZ2MSD600SN10#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.


Please download the latest datasheet of NFZ2MSD600SN10# from the official website of Murata


http://www.murata.com/en-sg/products/productdetail?partno=NFZ2MSD600SN10%23

"#"at the end indicates the package specification code.









Impedance-Frequency Characteristics

Derating of Rated Current

(Resistance element becomes dominant at high frequencies.)

Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

