

Product Search Data Sheet

Note: This datasheet may be out of date.

Please download the latest datasheet of CSTCG26M0V51-R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTCG26M0V51-R0

CSTCG26M0V51-R0










Applications

| Unsuitable | Please be sure to read and comply with | |
|--------------------------|--|--|
| Applications | these "Precautions for use." | |
| Specific Applications | Consumer equipment | |
| | Please refer to Our Website and | |
| | specifications, etc. for information about | |
| | the performance, functions, quality, | |
| | management, and safety required for | |
| | the above applications, and use | |
| | Products after confirming the | |
| | performance and reliability of the actual | |
| | Product. | |



Appearance & Shape







Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|---------------------|---------------------------------|
| R0 | 180mm Embossed Tape | 3000 |



Features

MURATA's package technology expertise has enabled the development of the Chip CERALOCK. High-density mounting can be realized because of the small package and the elimination of the need for an external load capacitor.

Features

- 1. Oscillation circuits do not require external load capacitors.
- 2. Available in a wide frequency range.
- 3. Extremely small and have a low profile.
- 4. No adjustment is necessary for oscillation circuits.

1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of CSTCG26M0V51-R0 from the official website of Murata $\,$ Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTCG26M0V51-R0

CSTCG26M0V51-R0



Specifications

| Draduct Tura | Ceramic Resonator | |
|-----------------------------|-------------------|--|
| Product Type | (CERALOCK) | |
| Series | CSTCG_V | |
| Frequency | 26.000MHz | |
| Frequency Tolerance | +/-0.50% max. | |
| Operating Temperature Range | -20°C~80°C | |
| | | |
| Frequency Shift by | +/-0.30% max. | |
| Temperature | , 0.00 % | |
| Frequency Aging | +/-0.20% max. | |
| Resonant Impedance (R1) | 50ohm max. | |
| Built-in Load Capacitance | 5pF | |
| (CL1/CL2) | <u>'</u> | |
| Shape | SMD | |
| Wash | Not available | |
| L x W (size) | 2.0x1.3mm | |
| Mass | 13mg | |
| | | |

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

