

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW21SN900SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW21SN900SQ2%23

"#"at the end indicates the package specification code.







< List of part numbers with package codes > DLW21SN900SQ2B DLW21SN900SQ2L



### **Applications**

Please be sure to read and comply with			
these "Precautions for use."			
Consumer equipment,Medical			
equipment [GHTF A/B/C] except for			
implant & surgery & auto injector,			
Industrial equipment except for			
transportation & facility & energy			
equipment			
Please refer to Our Website and			
specifications, etc. for information about			
the performance, functions, quality,			
management, and safety required for			
the above applications, and use			
Products after confirming the			
performance and reliability of the actual			
Product.			
Canalimar aguinment			
Consumer equipment			




### **Packaging Information**

			Standard
	Packaging	Specifications	Packing
			Quantity
	В	Bulk(Bag)	500
	L	180mm Embossed Tape	2000



## Appearance & Shape





1 of 4

#### Attentior

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW21SN900SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW21SN900SQ2%23

"#"at the end indicates the package specification code.



### **Features**

- 1. DLW21S series realizes small size and low profile. 2.0x1.2x1.2mm
- 2. High common mode impedance at high frequency effects excellent noise suppression performance.
- 3. Various common mode impedance items of 67 to 920 ohm can be used, considering noise level and signal frequency.
- 4. DLW21S series enables noise suppression for differential signal line without distortion in high speed signal transmission due to its high coupling.
- 5. Small dimension enables higher density packaging.

#### **Applications**

- 1. USB lines of PC, Peripheral equipment
- 2. LVDS lines of Note-PCs, LCDs
- 3. USB lines of Small digital AV equipment such as digital cameras

2 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW21SN900SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=DLW21SN900SQ2%23

"#"at the end indicates the package specification code.



## **Specifications**

Shape	SMD
	2012
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.2mm
Width Tolerance	±0.2mm
Thickness	1.2mm
Thickness Tolerance	±0.2mm
Common Mode Impedance (at 100MHz)	90Ω
Common Mode Impedance (at 100MHz) Tolerance	±25%
Rated Current	330mA
Derating of Rated Current	No
Rated Voltage	50Vdc
Withstanding Voltage	125Vdc
DC Resistance(max.)	0.35Ω
DC Resistance	0.35Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.011g
Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

3 of 4

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.




Note: This datasheet may be out of date.

Please download the latest datasheet of DLW21SN900SQ2# from the official website of Murata Manufacturing Co., Ltd.

"#"at the end indicates the package specification code.


# **Product Data**




10000 1000 (D) equippedul 100

Impedance-Frequency Characteristics Impedance-Frequency Characteristics (Main Items)

#### ■ Equivalent Circuit (Note 1)



Note1: The Port/Pin No. of the Simulation Model provided by our company is



**Equivalent Circuit** 

4 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

