

Product Search Data Sheet

NFP0QHB242HS2#

Note: This datasheet may be out of date. Please download the latest datasheet of NFP0QHB242HS2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=NFP0QHB242HS2%23

"#"at the end indicates the package specification code.

Discontinued Ro

RoHS REACH

< List of part numbers with package codes > NFP0QHB242HS2B NFP0QHB242HS2D




Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Medical	
	equipment [GHTF A/B/C] except for	
	implant & surgery & auto injector,	
	Industrial equipment except for	
	transportation & facility & energy	
	equipment	
Specific	Please refer to Our Website and	
Applications	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	O	
Applications	Consumer equipment	



Appearance & Shape





Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
D	180mm Paper Tape	15000



1. Small size and tight dimensional tolerance

Size: 0.65x0.50x0.30mm

Tolerance: +-0.05mm

- 2. Common mode noise suppression effect
- (The effect become maximum at 2.4GHz, 3.7GHz and 5.4GHz)
- 3. Prevents signal damaging in high speed differential lines.
- 4. Designed to match line impedance.

Application

High speed differential signal lines. HDMI,DVI,DisplayPort,USB3.0 etc.

- 1. Note PCs
- 2. Cellular phones
- 3. Digital Still Cameras, Digital Video Cameras

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





NFP0QHB242HS2#

Note: This datasheet may be out of date. Please download the latest datasheet of NFP0QHB242HS2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=NFP0QHB242HS2%23

"#"at the end indicates the package specification code.



Specifications

Shape	SMD
Size Code (in mm)	0605
Size Code (in inch)	025020
Length	0.65mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.3mm
Thickness Tolerance	±0.05mm
Common Mode Insertion Loss Characteristic	27dB Typ.(2.0GHz), 43dB Typ. (2.4GHz), 23dB Typ.(3.0GHz)
Rated Current	100mA
Derating of Rated Current	No
Rated Voltage	5Vdc
Withstanding Voltage	12.5Vdc
DC Resistance(max.)	2.21Ω
DC Resistance	1.7Ω±30%
Insulation Resistance(min.)	100ΜΩ
Cut-off Frequency	8.5GHz (Typ.)
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.4mg
Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.






NFP0QHB242HS2#


Note: This datasheet may be out of date. Please download the latest datasheet of NFP0QHB242HS2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=NFP0QHB242HS2%23


"#"at the end indicates the package specification code.

Product Data






Common Mode Insertion Loss Characteristic (Typical Value)



Common Mode Insertion Loss Characteristic (Main Items)(Typical Value)

Differential Mode Transmission Characteristics (Typical Value)



Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

without advance houce. Please check with our sales representatives or product engineers before order

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

