

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW32MH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW32MH101XK2%2

"#"at the end indicates the package specification code.

For A2B®









< List of part numbers with package codes > DLW32MH101XK2B DLW32MH101XK2L




Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Automotive powertrain/safety equipment,	
	Automotive infotainment/comfort	
	equipment,Consumer equipment,	
	Medical equipment [GHTF A/B/C]	
	except for implant & surgery & auto	
	injector,Industrial Equipment	
Specific	Please refer to Our Website and	
Applications	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive powertrain/safety equipment,	
Applications	A2B ®	



Appearance & Shape







Packaging Information

	Specifications	Standard
Packaging		Packing
		Quantity
В	Bulk(Bag)	500
L	180mm Embossed Tape	1500

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW32MH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW32MH101XK2%2

"#"at the end indicates the package specification code.



Features

- 1. Approved as noise suppression components by A2B® I/F.
- 2. High common mode impedance at high frequency range. So it is suitable for noise suppression through wide frequency range.
- 3. Wide operating temperature range meet automotive application. (-40 to +125 degrees C)

2 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW32MH101XK2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW32MH101XK2%2

"#"at the end indicates the package specification code.



Specifications

	OMB.
Shape	SMD
Size Code (in mm)	3225
Size Code (in inch)	1210
Length	3.2mm
Length Tolerance	±0.2mm
Width	2.5mm
Width Tolerance	±0.2mm
Thickness	2.5mm
Thickness Tolerance	max.
Rated Current	100mA
Derating of Rated Current	No
Rated Voltage	50Vdc
Withstanding Voltage	125Vdc
DC Resistance(max.)	3.36Ω
DC Resistance	2.8Ω±20%
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 125°C
Mass(typ.)	0.072g
Number of Circuit	1
Common Mode Inductance	100μH-30%/+50% (at 0.1MHz)
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

3 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW32MH101XK2# from the official website of Murata Manufacturing Co., Ltd.

"#"at the end indicates the package specification code.


Product Data






Impedance-Frequency Characteristics Impedance-Frequency Characteristics (Main Items)

■ Equivalent Circuit (Note 1)



Note1: The Port/Pin No. of the Simulation Model provided by our company is



Equivalent Circuit

4 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

