

### Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of CSTCG33M8V51-R0 from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=CSTCG33M8V51-B

# CSTCG33M8V51-R0










## **Applications**

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
Chaoifia	the performance, functions, quality,	
Specific Applications	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	



### Appearance & Shape







### Packaging Information

	Packaging	Specifications	Standard Packing Quantity
	R0	180mm Embossed Tape	3000



### **Features**

MURATA's package technology expertise has enabled the development of the Chip CERALOCK. High-density mounting can be realized because of the small package and the elimination of the need for an external load capacitor.

### Features

- 1. Oscillation circuits do not require external load capacitors.
- 2. Available in a wide frequency range.
- 3. Extremely small and have a low profile.
- 4. No adjustment is necessary for oscillation circuits.

1 of 2

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





### Product Search Data Sheet

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of CSTCG33M8V51-R0 from the official website of Murata

# CSTCG33M8V51-R0



# **Specifications**

Ceramic Resonator	
(CERALOCK)	
CSTCG V	
C31CG_V	
33.868MHz	
+/-0.50% max.	
-20°C~80°C	
-20 C 00 C	
+/-0.30% max.	
17-0.00 % max.	
+/-0.20% max.	
50ohm max.	
5pF	
Not available	
2.0x1.3mm	
13mg	

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

